

SPECIFICATION

TO ALL WHOM IT MAY CONCERN:

BE IT KNOWN THAT I, YOSHIKI YOSHIDA, a citizen of Japan residing at Kanagawa, Japan have invented certain new and useful improvements in

IMAGE FORMING APPARATUS, AN OPTICAL SCANNING APPARATUS  
AND AN IMAGE FORMING METHOD

of which the following is a specification:-

## BACKGROUND OF THE INVENTION

### 1. Field of the Invention

The present invention generally relates to image forming apparatuses and, more particularly, to an  
5 image forming apparatus using electrophotography such as a laser printer equipped with an optical scanner using a laser, a digital copy machine or a facsimile machine.

### 2. Description of the Related Art

Conventionally, there is a laser beam method  
10 as one of methods with which an image forming apparatus forms a visible image. According to the laser beam method used in an image forming apparatus, an optical scanning apparatus irradiates a laser beam onto a photoconductor (a medium to be scanned) so as to form an  
15 image.

A description will be given below, with reference to FIG. 1, of an image forming operation performed by an image forming apparatus using a conventional laser beam method. FIG. 1 is an  
20 illustration for explaining an image forming operation performed by an image forming apparatus using a conventional laser beam method.

In the image forming apparatus, an electric charger (not shown in the figure) such as a roller-type  
25 contact charger uniformly charges a photoconductor. A

laser light source irradiates a laser beam onto a rotating polygon mirror (rotational polygon mirror). The polygon mirror deflects periodically the laser beam projected from the laser light source. The laser beam  
5 passes through a  $f\theta$  lens and scans a surface of the photoconductor in a main scanning direction while the photoconductor is moving or rotating in a sub-scanning direction. Static electricity in portions of the surface of the photoconductor onto which the laser beam  
10 is irradiated is removed by the laser beam, thereby forming a pattern of static electricity (electrostatic latent image) on the surface of the photoconductor.

It should be noted that a controller (not shown in the figure) sends image data corresponding to  
15 each page to a laser drive circuit as an image signal (video signal) on an individual line (one scanning line) basis. Then, the laser drive circuit performs a modulating operation by outputting the image signal to the laser light beam in synchronization with a pixel  
20 clock (write clock). The pixel clock is supplied to the laser drive circuit from a pixel clock generating circuit (not shown in the figure) via a phase synchronization circuit (not shown in the figure). The pixel clock generating circuit and the phase  
25 synchronization signal constitute image clock generating

means and phase setting means.

A description will now be given, with reference to FIG. 2, of a relationship between the pixel clock and the phase change (phase setting) of the pixel  
5 clock. FIG. 2 is a timing chart showing a relationship between a conventional pixel clock and a phase change thereof.

A pixel clock generating circuit generates and outputs a pixel clock  $clk_w$  in synchronization with a  
10 synchronization detection signal supplied by a synchronous detection sensor. The pixel clock  $clk_w$  is generated from a reference clock  $clk_o$  (an original clock generated by an oscillator (not shown in the figure)), which is  $n$  times (four times in FIG. 2) of the frequency  
15 of the pixel clock  $clk_w$ , by toggling the reference clock  $clk_o$  to a high level (H) and a low level (L) at each 4 pulses of  $clk_o$  according to a counting control. In the above-mentioned optical scanning apparatus, when forming beam spots of the laser beam on the surface to be  
20 scanned so as to write an electrostatic latent image, the write density of the beam spots is adjusted to be uniform.

However, if an environmental fluctuation such as a temperature change, etc. arises in the atmosphere  
25 of the  $f\theta$  lens, the  $f\theta$  lens is distorted, which results



in a change in an index of refraction. Additionally, if an environmental fluctuation such as a temperature change, etc. arises in the atmosphere of the laser light source, the wavelength of the laser beam emitted by the laser light source is changed. Therefore, the  $f\theta$  lens is configured and arranged to refract the laser beam at a predetermined angle according to the wavelength of the laser beam incident thereon. For this reason, as shown in FIG. 1, an error occurs in the refractive angle of the laser beam incident on the  $f\theta$  lens. Such an error in the refractive angle causes an error in a write magnification per one main scanning period of the laser beam by the polygon mirror, which may give an undesired influence to an output image. In order to eliminate such an undesired influence, a phase change to shift the phase of the pixel clock  $clk_w$  is performed so as to correct the write magnification of the laser beam.

In the above-mentioned optical scanning apparatus, the pixel clock generating circuit performs a phase control using an external pulse train  $xpls$  so as to perform the phase change to shift the phase of the pixel clock  $clk_w$ . There are two kinds of pulse train as the external pulse train  $xpls$ , one is an external pulse train  $xpls_p$  for advancing the phase of the pixel clock  $clk_w$  and the other is an external pulse train  $xpls_m$  for

delaying the phase of the pixel clock  $clk_w$ . For example, in a case in which the pixel clock  $clk_w$  is generated from the reference clock  $clk_o$ , the pixel clock  $clk_w$ , which is usually generated with 8 pulses of  $clk_o$ , is  
5 generated with 9 pulses of  $clk_o$  or 7 pulses of  $clk_o$  by increasing or decreasing the number of count of the pulses of the external pulse train  $xplsp$  or  $xplsm$ . By changing the number of counts by increasing or decreasing the number of counts, the frequency of the  
10 pixel clock  $clk_w$  is made  $8/7$  times (an advance control) or  $8/9$  times (a delay control), which can shift the pixel clock  $clk_w$  after the phase change. This provides an effect in view of one main scanning line that an entire magnification is increased or decreased as  $T_m - 7/8$   
15 (advancing control) or  $T_m + 9/8$  (delay control), where  $T_m$  is a total time of main scanning of one line. Thus, the optical scanning apparatus can form an image on a desired position on the photoconductor without being influenced by the environment fluctuation.

20           Moreover, the pixel clock generating circuit is provided with a pulse generating circuit which generates the above-mentioned external pulse train  $xpls$ . The pulse generating circuit generates the external pulse train (hereinafter, may be simply referred to as  
25 pulses)  $xpls$  in response to positions at which the phase

change is to be applied to the pulse train of the pixel clock clkw.

A description will now be given, with reference to FIG. 3, of an operation of generating the external pulse train by the pulse generating circuit. FIG. 3 is a block diagram of a conventional pulse generating circuit.

The pulse generating circuit shown in FIG. 3 comprises comparators 1001 and 1002 and counters 1003 and 1004.

In the pulse generating circuit, a pulse generation interval (period) is set to the comparator 1001 and a pulse number num is set to the comparator 1002 by an engine CPU (not shown in the figure) so as to perform the following operation when one scan of a laser beam is performed in the main scanning direction by the polygon mirror.

The counter 1003 starts a counting operation to count a number of pulses of the pixel clocks clkw (count value i) in accordance with an input of a clear signal xlclr generated from a synchronization detection signal by a circuit, which is not shown in the figure, at a time of input of the clear signal xlclr as a reference, and stops the counting operation when a stop signal is supplied by the comparator 1002. The

comparator 1001 compares the count value  $i$  of the counter 1003 with the previously set pulse generation interval (hereinafter, may be referred to as a setting value)  $prd$ , and generates the pulse  $xpls$  each time the  
5 count value  $i$  reaches the setting value  $prd$ . The counter 1004 counts the number (count value  $j$ ) of the pulses  $xpls$  generated by the comparator 1001. The comparator 1002 compares the count value  $j$  of the counter 1004 with the previously set pulse number  
10 (hereinafter, may be referred to as a setting value)  $num$ , and generates the stop signal when the count value  $j$  reaches the setting value  $num$ .

FIG. 4 is a flowchart of an operation of the pulse generating circuit shown in FIG. 3. A description  
15 will now be given, with reference 3 to FIGS. 3 and 4, of an operation of generating the external pulse train  $xpls$  performed by the conventional pulse generating circuit.

First, counters 1003 and 1004 reset count values  $i$  and  $j$  to "1", respectively, when a power supply  
20 to the pulse generating circuit is turned on (step S1001).

Thereafter, the counter 1003 waits for an input of a clear signal  $xlclr$  (No of step S1002), and after the clear signal  $xlclr$  is input (Yes of step  
25 S1002), the counter 1003 counts up (+1) the count value

i each time a pulse of the pixel clock clkw is input.

A comparator 1001 performs the process of step S1003 until the count value i reaches the setting value prd (No of step S1004).

5           The comparator 1001 will generate the pulse xpls, when the count value i reaches the setting value prd (Yes of step S1004). The counter 1003 returns the count value i to "1" according to the input of the pulse xpls (step S1005).

10           Additionally, as a result of the comparison between the count value j of the counter 1004 and the setting value num by the comparator 1002 (step S1006), if the count value j has not reached the setting value num (No of step S1006), the counter 1004 counts up (+1)  
15 the count value j according to the input of the pulse xpls (step S1007).

          Thereafter, the counters 1003 and 1004 and the comparator 1001 repeat the above-mentioned operation, and the comparator 1002 generates a stop signal when the  
20 count value j reaches the setting value num. Thus, the pulse generating circuit ends the operation (hereinafter, this operation is referred to as "pulse generating operation").

          Here, Japanese Patent No. 3315474 discloses a  
25 conventional technique related with a phase control of

the pixel clock in an image forming apparatus. In the image forming apparatus disclosed in this patent document, there are provided a plurality of detection sensors that detect a laser beam moving in a main-scanning direction, and a scanning time or a count number of the clock is measured from a time when the laser beam is detected by one of the detection sensors and until the laser beam is detected by another one of the detection sensors so as to correct a write clock frequency in accordance with the result of the measurement.

Additionally, there is a multi-beam method for forming an image on a photoconductor using more than two laser light sources among laser beam methods for forming an image by irradiating a laser beam onto a scan surface of a photoconductor.

The image forming apparatus using the multi-beam method increases a speed of forming a latent image by writing beam spots on more than two main-scanning lines simultaneously.

FIG. 5 is an illustration showing an image forming operation performed by a conventional image forming apparatus using the multi-beam method. FIG. 5 shows an example in which two laser beams are irradiated by two laser light sources LD0 and LD1. As shown in FIG.

5, the two laser light sources LD0 and LD1 irradiate laser beams onto a rotating polygon mirror. The polygon mirror deflects periodically the laser beams projected from the laser light sources LD0 and LD1. The deflected  
5 laser beams transmit through a  $f\theta$  lens and repeatedly scan a surface of a photoconductor to be scanned that is rotating in a sub-scanning direction while uniformly charging the surface of the photoconductor. Portions irradiated by the laser beams on the photoconductor are  
10 electrically discharged, thereby forming an electrostatic latent image.

Japanese Laid-Open Patent Application No. 2000-166598 discloses a multi-beam light source apparatus and an optical scan apparatus using the above-  
15 mentioned multi-beam method. In this patent document, there are provided two light source parts each of which has two light source elements, and an offset of projecting axes of the two light source parts is corrected by adjusting a relative angle of light beams  
20 projected from the two light sources.

However, there are the following problems in the image forming apparatus using the multi-beam method in which a plurality of laser light sources shares a single optical system and a single image carrier.

25 As mentioned above, a fluctuation occurs in

the refraction index of a group of lenses including the  $f_0$  lens and the wavelength of the laser beams projected from the laser light sources. Therefore, an error occurs in the write magnification of each of the laser  
5 beams projected from the plurality of laser light beams per one scanning period, and, thus, there is a problem in that positions of the images written by the laser light beams are shifted from each other. Consequently, a line extending in the sub-scanning direction appears  
10 as it wobbles and a noise is generated in an entire image, and, thus, there is a problem in that an unclear image is formed.

Additionally, the group of lenses including the  $f_0$  lens forming an optical system are made in  
15 consideration of refraction of a specific wavelength. Therefore, if a plurality of laser light sources share a single optical system and a single image carrier in the image forming apparatus using the multi-beam method, a plurality of laser beams that emit laser beams having  
20 the same wavelength must be selected and provided in the image forming apparatus.

However, it is difficult to prepare a certain number of laser light sources that emit laser beams having accurately the same wavelength, and, thus, there  
25 is a problem in that the formed image is unclear.



SUMMARY OF THE INVENTION

It is a general object of the present invention to provide an improved and useful image forming apparatus in which the above-mentioned problems are eliminated.

A more specific object of the present invention is to provide an image forming apparatus which is capable of forming a clear image by using laser beams projected from a plurality of laser light sources.

In order to achieve the above-mentioned objects, there is provided according to one aspect of the present invention an image forming apparatus that forms an electrostatic latent image on a medium to be scanned by laser beams, which are projected from a plurality of laser light sources and periodically deflected by a rotational deflecting unit, so that the laser beams scan the medium, which is uniformly charged and moving in a sub-scanning direction, in a main-scanning direction perpendicular to the sub-scanning direction, the image forming apparatus comprising: a pixel clock generating unit that generates pixel clocks, which are used for controlling timings of projection of the laser beams, separately for each of the laser light sources, and for performing a phase change of each of

the pixel clocks; and a phase control unit that controls independently each of the pixel clocks.

In the above-mentioned image forming apparatus, the phase control unit may generate control pulse  
5 signals for controlling the phase change of the pixel clocks generated by the pixel clock generation means, respectively, and may output the control pulse signals to the pixel clock generation means, and the pixel clock  
generating unit may perform the phase change of the  
10 pixel clocks when the control pulse signals are supplied thereto.

The image forming apparatus according to the present invention may further comprise an operation unit that inputs setting values, which indicate an interval  
15 and a number of pulses of the control pulse signals for each of the laser light sources, wherein the phase control unit generates the control pulse signals of the pixel clocks, respectively, based on the setting values input by the operation unit, and outputs the control  
20 pulse signals to the pixel clock generating unit.

The image forming apparatus according to the present invention may further comprise: an operation unit that inputs setting values, which indicate an interval and a number of pulses of the control pulse  
25 signals for performing the phase change on one of the

laser light sources; and a setting value computing units that computes setting values for other laser light sources other than the one of the laser light sources by adding values, which is previously specified for each of the other laser light sources, to the setting values for the one of the laser light sources input by the operation unit, wherein the phase control unit generates and outputs the control pulse signals corresponding to the respective laser light sources based on the setting values input by the operation means and the setting values computed by the setting value computing unit.

The image forming apparatus according to the present invention may further comprise a synchronization detection unit that detects the laser beams from the laser light sources at a position outside an image formation area where the electrostatic latent image is formed on the medium to be scanned in the main-scanning direction and for outputting a synchronization detection signals, which specify scan start positions of the laser beams in the main-scanning direction, respectively, wherein the pixel clock generating unit generates the pixel clocks in synchronization with the synchronization detection signals.

The image forming apparatus according to the present invention may further comprise: a

synchronization detection unit that detects the laser beams from the laser light sources at positions outside an image formation area where the electrostatic latent image is formed on the medium to be scanned in the main-  
5 scanning direction, the synchronization detection unit including a first synchronization detection unit and a second synchronization detection unit located opposite to the first synchronization detection unit with respect to the image formation area; a scan time measuring unit  
10 that measures a scan time after the first synchronization detection unit detects the laser beam until the second synchronization detection unit detects the laser beam on an individual laser light source basis; and a scan time comparison unit that compares the  
15 scan time of each of the laser light sources measured by the scan time measuring unit with a value indicating a reference of the scan time so as to compute setting values based on a result of the comparison, the setting values indicating an interval and a number of pulses of  
20 each of the control pulse signals, wherein the phase control unit generates and outputs the control pulse signals corresponding to the respective laser light sources base on the setting values computed by the scan time comparison unit.

25 In the above-mentioned image forming apparatus,

the scan time comparison unit may compute a number of pulses to be increased or decreased with respect to each of the control pulse signals by multiplying a value, which is obtained by subtracting the reference of the scan time from the measured scan time, by a period of a  
5    respective one of the pixel clocks and dividing the multiplied value by a time unit of the phase change.

          Additionally, in the above-mentioned image forming apparatus, the synchronization detection unit  
10   may detect the laser beams from the laser light sources, respectively, at a position outside an image formation area where the electrostatic latent image is formed on the medium to be scanned in the main-scanning direction so as to output synchronization detection signals, which  
15   specify scan start positions of the respective laser beams in the main-scanning direction, and the pixel clock generating unit generates the pixel clocks in synchronization with the synchronization detection signals.

20           The image forming apparatus according to the present invention may further comprise: a synchronization detection unit that detects the laser beams from the laser light sources at positions outside an image formation area where the electrostatic latent  
25   image is formed on the medium to be scanned in the main-

scanning direction, the synchronization detection unit including a first synchronization detection unit and a second synchronization detection unit located opposite to the first synchronization detection unit with respect  
5 to the image formation area; a scan time measuring unit that measures a scan time after the first synchronization detection unit detects the laser beam until the second synchronization detection unit detects the laser beam on an individual laser light source  
10 basis; and a scan time comparison unit that compares the scan time of each of the laser light sources measured by the scan time measuring unit with a value indicating a reference of the scan time so as to compute setting values for the one of the laser light sources based on a  
15 result of the comparison, the setting values indicating an interval and a number of pulses of the control pulse signal of the one of the laser light sources; and a setting value computing unit that computes each of the setting values of the other laser light sources by  
20 adding setting values, which is previously specified for each of the other laser light sources, to the setting values for the one of the laser light sources, wherein the phase control unit outputs the control pulse signals corresponding to the other laser light sources base on  
25 the setting values computed by the setting value

computing unit.

In the above-mentioned image forming apparatus, the scan time comparison unit may compute a number of pulses to be increased or decreased with respect to each of the control pulse signals by multiplying a value, which is obtained by subtracting the reference of the scan time from the measured scan time, by a period of a respective one of the pixel clocks and dividing the multiplied value by a time unit of the phase change.

10 In the above-mentioned image forming apparatus, the synchronization detection unit may detect the laser beams from the laser light sources, respectively, at a position outside an image formation area where the electrostatic latent image is formed on the medium to be scanned in the main-scanning direction so as to output synchronization detection signals, which specify scan start positions of the respective laser beams in the main-scanning direction, and the pixel clock generating unit may generate the pixel clocks in synchronization with the synchronization detection signals.

20 In the image forming apparatus according to the present invention, the phase control unit may control a phase of each of the pixel clocks so that the phase is changed by a time unit shorter than a period of each of the pixel clocks.

In the image forming apparatus according to the present invention, the phase control unit may vary an output timing of the control pulse signals for each scan period.

5           In the above-mentioned image forming apparatus, the phase control unit may vary the output timing of the control pulse signals by a fixed unit time each time when one scan period has passed.

          In the above-mentioned image forming apparatus,  
10 the phase control unit may vary the output timing of the control pulse signals based on the unit time that is obtained as a product of a value, which is obtained by subtracting a product of the interval of pulses and the number of pulses of each of the control signal pulses  
15 from the scan period, and a product of a fractional number having a numerator of a positive integer and a denominator of a positive integer, and wherein the output timing of the control pulse signals after change matches the output timing before change for the number  
20 of the denominator.

          The image forming apparatus according to the present invention, the phase control unit may vary a phase of each of the pixel clocks for each divided period obtained by dividing one scan period of each of  
25 the laser light sources.



Additionally, there is provided according to another aspect of the present invention an image forming apparatus that forms an electrostatic latent image on a medium to be scanned by laser beams, which are projected from a plurality of laser light sources and periodically deflected by a rotational deflecting unit, so that the laser beams scan the medium, which is uniformly charged and moving in a sub-scanning direction, in a main-scanning direction perpendicular to the sub-scanning direction, the image forming apparatus comprising: a pixel clock generating unit that generates pixel clocks for performing independently a modulation control of each of the laser light sources, and changes independently a phase of each of the pixel clocks of the laser light sources based on control pulse signals supplied thereto.

The above-mentioned image forming apparatus may further comprise a synchronization detection unit that detects the laser beams from the laser light sources at a position outside an image formation area where the electrostatic latent image is formed on the medium to be scanned in the main-scanning direction and for outputting a synchronization detection signals, which specify scan start positions of the laser beams in the main-scanning direction, respectively, wherein the

pixel clock generating unit may generate the pixel clocks in synchronization with the synchronization detection signals.

In the above-mentioned optical scanning apparatus, the synchronization detection unit may detect the laser beams at two positions outside the image formation area in the main-scanning direction, and may output the synchronization detection signals for measuring a scan time spent on scanning between the two positions.

In the above-mentioned image forming apparatus, the pixel clock generating unit may control a phase of each of the pixel clocks so that the phase is changed by a time unit shorter than a period of each of the pixel clocks.

In the above-mentioned image forming apparatus, the pixel clock generating unit may vary an output timing of the control pulse signals for each scan period.

In the above-mentioned image forming apparatus, the pixel clock generating unit may vary the output timing of the control pulse signals by a fixed unit time each time when one scan period has passed.

In the above-mentioned image forming apparatus, the pixel clock generating unit may vary the output timing of the control pulse signals based on the unit

time that is obtained as a product of a value, which is obtained by subtracting a product of the interval of pulses and the number of pulses of each of the control signal pulses from the scan period, and a product of a  
5 fractional number having a numerator of a positive integer and a denominator of a positive integer, and wherein the output timing of the control pulse signals after change matches the output timing before change for the number of the denominator.

10           Additionally, there is provided according to another aspect of the present invention an image forming method that forms an electrostatic latent image on a medium to be scanned by laser beams, which are projected from a plurality of laser light sources and periodically  
15 deflected in a rotational deflecting process, so that the laser beams scan the medium, which is uniformly charged and moving in a sub-scanning direction, in a main-scanning direction perpendicular to the sub-scanning direction, the image forming apparatus  
20 comprising: a pixel clock generation step of generating pixel clocks, which are used for controlling timings of projection of the laser beams, separately for each of the laser light sources; a phase control step of controlling independently a phase control of each of the  
25 pixel clocks; and a phase change step of performing the

phase change of each of the pixel clocks in accordance with the phase control step.

In the above-mentioned image forming method, the phase control step may generate control pulse  
5 signals for controlling the phase change of the pixel clocks generated in the pixel clock generation step, respectively, and outputs the control pulse signals to the pixel clock generation step, and the pixel clock  
generation step may perform the phase change of the  
10 pixel clocks when the control pulse signals are supplied thereto.

The image forming method according to the present invention may further comprise an input step of inputting setting values, which indicate an interval and  
15 a number of pulses of the control pulse signals for each of the laser light sources, wherein the phase control step generates the control pulse signals of the pixel clocks, respectively, based on the setting values input in the input step, and outputs the control pulse signals  
20 to the pixel clock generation step.

The above-mentioned image forming method may further comprise a synchronization detection step of detecting the laser beams from the laser light sources at a position outside an image formation area where the  
25 electrostatic latent image is formed on the medium to be

scanned in the main-scanning direction and outputting a  
synchronization detection signals, which specify scan  
start positions of the laser beams in the main-scanning  
direction, respectively, wherein the pixel clock  
5 generation step may generate the pixel clocks in  
synchronization with the synchronization detection  
signals.

The image forming method according to the  
present invention may further comprise: an input step of  
10 inputting setting values, which indicate an interval and  
a number of pulses of the control pulse signals for  
performing the phase change on one of the laser light  
sources; and a setting value computation step of  
computing setting values for other laser light sources  
15 other than the one of the laser light sources by adding  
values, which is previously specified for each of the  
other laser light sources, to the setting values for the  
one of the laser light sources input in the input step,  
wherein the phase control step generates and outputs the  
20 control pulse signals corresponding to the respective  
laser light sources based on the setting values input in  
the input step and the setting values computed in the  
setting value computation step.

The above-mentioned image forming method  
25 further comprise a synchronization detection step of

detecting the laser beams from the laser light sources  
at a position outside an image formation area where the  
electrostatic latent image is formed on the medium to be  
scanned in the main-scanning direction and outputting a  
5   synchronization detection signals, which specify scan  
start positions of the laser beams in the main-scanning  
direction, respectively, wherein the pixel clock  
generation step may generate the pixel clocks in  
synchronization with the synchronization detection  
10   signals.

          The image forming method according to the  
present invention may further comprise: a first  
synchronization detection step of detecting the laser  
beams from the laser light sources at a first position  
15   outside an image formation area where the electrostatic  
latent image is formed on the medium to be scanned in  
the main-scanning direction; a second synchronization  
detection step of detecting the laser beams from the  
laser light sources at a second position outside the  
20   image formation area; a scan time measuring step of  
measuring a scan time after the laser beam is detected  
in the first synchronization detection step and until  
the laser beam is detected in the second synchronization  
detection step on an individual laser light source  
25   basis; and a scan time comparison step of comparing the

scan time of each of the laser light sources measured by the scan time measuring means with a value indicating a reference of the scan time so as to compute setting values based on a result of the comparison, the setting values indicating an interval and a number of pulses of each of the control pulse signals, wherein the phase control step generates and outputs the control pulse signals corresponding to the respective laser light sources base on the setting values computed in the scan time comparison step.

In the above-mentioned image forming method, the scan time comparison step may compute a number of pulses to be increased or decreased with respect to each of the control pulse signals by multiplying a value, which is obtained by subtracting the reference of the scan time from the measured scan time, by a period of a respective one of the pixel clocks and dividing the multiplied value by a time unit of the phase change.

In the above-mentioned image forming method, the first synchronization detection means may detect the laser beams from the laser light sources, respectively, at the first position so as to output synchronization detection signals, which specify scan start positions of the respective laser beams in the main-scanning direction, and the pixel clock generation step generates

the pixel clocks in synchronization with the synchronization detection signals.

The image forming method according to the present invention may further comprise: a first

5   synchronization detection step of detecting the laser beams from the laser light sources at a first position outside an image formation area where the electrostatic latent image is formed on the medium to be scanned in the main-scanning direction; a second synchronization

10   detection step of detecting the laser beams from the laser light sources at a second position outside the image formation area; a scan time measuring step of measuring a scan time after the laser beam is detected in the first synchronization detection step and until

15   the laser beam is detected in the second synchronization detection step on an individual laser light source basis; a scan time comparison step of comparing the scan time of each of the laser light sources measured in the scan time measuring step with a value indicating a

20   reference of the scan time so as to compute setting values for the one of the laser light sources based on a result of the comparison, the setting values indicating an interval and a number of pulses of the control pulse signal of the one of the laser light sources; and a

25   setting value computation step of computing each of the



setting values of the other laser light sources by adding setting values, which is previously specified for each of the other laser light sources, to the setting values for the one of the laser light sources, wherein  
5 the phase control step outputs the control pulse signals corresponding to the other laser light sources base on the setting values computed in the setting value computation step.

In the above-mentioned image forming method,  
10 the scan time comparison step may compute a number of pulses to be increased or decreased with respect to each of the control pulse signals by multiplying a value, which is obtained by subtracting the reference of the scan time from the measured scan time, by a period of a  
15 respective one of the pixel clocks and dividing the multiplied value by a time unit of the phase change.

In the above-mentioned image forming method, the scan time comparison step may compute a number of pulses to be increased or decreased with respect to each  
20 of the control pulse signals by multiplying a value, which is obtained by subtracting the reference of the scan time from the measured scan time, by a period of a respective one of the pixel clocks and dividing the multiplied value by a time unit of the phase change.

25 In the image forming method according to the

present invention, the phase control step may control a phase of each of the pixel clocks so that the phase is changed by a time unit shorter than a period of each of the pixel clocks.

5                   In the image forming method according to the present invention, the phase control step may vary an output timing of the control pulse signals for each scan period.

                  In the above-mentioned image forming method,  
10   the phase control step may vary the output timing of the control pulse signals by a fixed unit time each time when one scan period has passed.

                  In the above-mentioned image forming method,  
the phase control step may vary the output timing of the  
15   control pulse signals based on the unit time that is obtained as a product of a value, which is obtained by subtracting a product of the interval of pulses and the number of pulses of each of the control signal pulses from the scan period, and a product of a fractional  
20   number having a numerator of a positive integer and a denominator of a positive integer, and wherein the output timing of the control pulse signals after change matches the output timing before change for the number of the denominator.

25                   In the image forming method according to the

present invention, the phase change step may vary a phase of each of the pixel clocks for each divided period obtained by dividing one scan period of each of the laser light sources.

5           Other objects, features and advantages of the present invention will become more apparent from the following detailed description when read in conjunction with the accompanying drawings.

10    BRIEF DESCRIPTION OF THE DRAWINGS

FIG. 1 is an illustration for explaining an image forming operation performed by an image forming apparatus using a conventional laser beam method;

15           FIG. 2 is a timing chart showing a relationship between a conventional pixel clock and a phase change thereof;

FIG. 3 is a block diagram of a conventional pulse generating circuit;

20           FIG. 4 is a flowchart of an operation of the pulse generating circuit shown in FIG. 3;

FIG. 5 is an illustration for explaining an image forming operation performed by a conventional image forming apparatus using the multi-beam method;

25           FIG. 6 is a block diagram of an image forming apparatus according to a first embodiment of the present

invention;

FIG. 7A is an illustration showing a positional relationship between two laser light sources in the first embodiment of the present invention;

5           FIG. 7B is an illustration for explaining laser beam irradiation by the laser light sources in the first embodiment of the present invention;

FIG. 8 is a flowchart of an image forming operation performed by the image forming apparatus  
10 according to the first embodiment of the present invention;

FIG. 9 is a timing chart showing an example of a relationship between a pixel clock and a phase change thereof;

15           FIG. 10 is a block diagram of pulse train generating units according to the first embodiment of the present invention;

FIG. 11 is a flowchart of an operation of the pulse train generating units according to the first  
20 embodiment of the present invention;

FIG. 12 is a timing chart showing a relationship between a clear signal and an external pulse train according to the first embodiment of the present invention;

25           FIG. 13 is a block diagram of an image forming

apparatus according to a second embodiment of the present invention;

FIG. 14 is a time chart showing signals output from a front-end synchronization detection unit and a rear-end synchronization detection unit according to the second embodiment of the present invention;

FIG. 15A is an illustration showing a positional relationship between two laser light sources according to the second embodiment of the present invention;

FIG. 15B is an illustration showing laser beam irradiation by the laser light sources according to the second embodiment of the present invention;

FIG. 16 is a block diagram of scan time measuring units according to the second embodiment of the present invention;

FIG. 17 is a flowchart of a phase adjusting operation of a pixel clock performed by the image forming apparatus according to the second embodiment of the present invention;

FIG. 18 is a block diagram of an image forming apparatus according to a third embodiment of the present invention;

FIG. 19 is an illustration showing a setting operation of setting values of laser light sources

according to the third embodiment of the present invention;

FIG. 20 is a flowchart of the setting operation of the setting values of the laser light sources according to the third embodiment of the present invention;

FIG. 21 is a block diagram of an image forming apparatus according to a fourth embodiment of the present invention;

10           FIG. 22 is a flowchart of a setting operation of the setting values performed by the image forming apparatus according to the third embodiment of the present invention;

15           FIG. 23 is a block diagram of an image forming apparatus according to a fifth embodiment of the present invention;

FIG. 24 is a block diagram of shift generating units according to the fifth embodiment of the present invention;

20           FIG. 25 is a block diagram of pulse train generating units according to the fifth embodiment of the present invention;

FIG. 26 is a time chart showing an expel of a shift of an external pulse train;

25           FIG. 27 is a time chart showing another

example of a shift of the external pulse train;

FIG. 28 is a block diagram of an image forming apparatus according to a sixth embodiment of the present invention;

5               FIG. 29 is a circuit diagram of a pulse generating unit according to the sixth embodiment;

FIG. 30 is a circuit diagram of another pulse generating unit according to the sixth embodiment;

FIG. 31 is a flowchart of an operation of  
10               generating pulses performed by the pulse generating unit according to the sixth embodiment of the present invention;

FIG. 32 is an illustration showing a pulse train an containing external pulse train in the sixth  
15               embodiment;

FIG. 33 is a block diagram of an image forming apparatus according to a seventh embodiment of the present invention;

FIG. 34 is a block diagram of an image forming  
20               apparatus according to an eighth embodiment of the present invention;

FIG. 35 is a block diagram of an image forming apparatus according to a ninth embodiment of the present invention;

25               FIG. 36 is a block diagram of an image forming

apparatus according to a tenth embodiment of the present invention;

FIG. 37 is a block diagram of an image forming apparatus according to an eleventh embodiment of the  
5 present invention; and

FIG. 38 is a block diagram of an image forming apparatus according to a twelfth embodiment of the present invention.

## 10 DETAILED DESCRIPTION OF THE PREFERRED EMBODIMENTS

### (First Embodiment)

A description will now be given of an image forming apparatus according to a first embodiment of the present invention. The image forming apparatus  
15 according to the present embodiment forms an electrostatic latent image on a surface of a medium that is uniformly charged and moving in a sub-scanning direction by scanning laser beams projected from a plurality of laser light sources in a main-scanning  
20 direction, which is perpendicular to the sub-scanning direction. The image forming apparatus independently generates pixel clocks, which is used for timing control of emission of each of the laser light sources, for each of the laser light beams, and performs a phase change  
25 control of each pixel clock independently.



A description will be given below, with reference to FIG. 6, of a structure of the image forming apparatus according to the present invention. FIG. 6 is a block diagram of the image forming apparatus according to the first embodiment of the present invention.

As shown in FIG. 6, the image forming apparatus comprises an optical scanning apparatus 10, a data control apparatus 20, a central processing unit (CPU) 30, a printer controller 40, and an operation unit 50 as an input means. It should be noted that the structure of the image forming apparatus shown in FIG. 6 is simplified for the sake of easy understanding, and may comprises structural elements other than that shown in FIG. 6.

The optical scanning apparatus 10 is a unit that forms an image using laser beams. The optical scanning apparatus 10 comprises a photoconductor 11 serving as a medium to be scanned, an  $f\theta$  lens 12, a polygon mirror 13, laser light source drivers 14a and 14b, synchronization detection driver 15 and laser light sources LD0 and LD1.

Each of the laser light sources LD0 and LD1 is an element that emits a laser beam, and can be a light-emitting element such as a laser diode.

The photoconductor 11 is formed of a material

(a layer of an optical semiconductor) having an electric characteristic that is changeable by irradiation of a light onto a surface thereof. For example, the photoconductor can be a photoconductor drum 11 that  
5 rotates in a sub-scanning direction.

The  $f\theta$  lens 12 is provided for forming an image on a surface of the photoconductor 11 by focusing the laser beams reflected by the polygon mirror 13. The  $f\theta$  lens 12 deflects the laser beams having a specific  
10 wavelength at a predetermined refraction angle.

The polygon mirror 13 is a mirror having a polyhedral shape that is rotatable at a constant speed by a motor (not shown in the figure). The polygon mirror 13 changes the reflection angle of the laser beams  
15 projected from the laser light sources LD0 and LD1 in accordance with a rotation thereof so that scan the laser beams on the surface of the photoconductor 11 to be scanned in the main-scanning direction.

Laser light source drivers 14a and 14b drive  
20 the laser light sources LD0 and LD1, respectively, and operate according to image signals from the data control apparatus 20. More specifically, after the laser beams are detected by the synchronization detection unit 15 and a predetermined time has passed after a  
25 synchronization detection signal detp is supplied from

the synchronization detection unit 15 to the data control apparatus 20, the laser light source drivers 14a and 14b start a modulation (ON/OFF) control of the laser light sources LD0 and LD1 in accordance with the image  
5 signals from the data control apparatus 20 so as to emit the laser beams, respectively. Thus, if there is a variation in an angle between adjacent reflection surfaces of the polygon mirror 13, a write start position can always be at the same position of the  
10 surface to be scanned and a write end position can always be at the same position.

The synchronization detection unit 15 is provided outside an image area of the surface of the photoconductor 11 to be scanned along a path of the  
15 laser beams in the main-scanning direction (for example, immediately before or after the scanning start position) so as to detect the laser beams passed through the f $\theta$  lens 12 and irradiated thereon. Upon detection of the laser beams, the synchronization detection unit 15  
20 generates the synchronization detection signal detp, which defines the write start position of the laser beams in the main-scanning direction for always set the write start position at the same point on the surface to be scanned, and outputs the signal detp to the data  
25 control apparatus 20.

The data control apparatus 20 outputs image signals for controlling the laser light source drivers 14a and 14b so as to control the laser beam write operation by the optical scanning apparatus 10. The data control apparatus 20 comprises pulse train generating units 21a and 21b serving as phase control means, clock generating units 22a and 22b serving as pixel clock generating means, an image data processing unit 23, and a register 24.

The clock generating unit 22a generates a pixel clock  $clk_w0$  in synchronization with the synchronization signal detection signal  $detp$  supplied by the synchronization detection unit 15, and outputs the pixel clock  $clk_w0$  to the pulse generating unit 21a and the image data processing unit 23. The clock generating unit 22a generates the pixel clock  $clk_w0$  by toggling a high level (H) and a low level (L) of a reference clock (original clock)  $clk_o0$ , which is generated by an oscillator (not shown in the figure) provided in the clock generating unit 22a and has a frequency M times the frequency of the pixel clock  $clk_w0$ . Thus, it is possible to arrange the scan start position of each scanning line on the photoconductor 11 at the same position. Additionally, upon detection of the synchronization detection signal  $detp$  input from the

synchronization detection section 15, the clock generating unit 22a outputs a clear signal xlclr0 to the pulse train generating unit 21a.

The clock generating unit 22b generates a  
5 pixel clock clkw0 in synchronization with the  
synchronization signal detection signal detp supplied by  
the synchronization detection unit 15, and outputs the  
pixel clock clkwl to the pulse train generating unit 21b  
and the image data processing unit 23. The clock  
10 generating unit 22b generates a pixel clock clkwl by  
toggling a high level (H) and a low level (L) of a  
reference clock (original clock) clkol, which is  
generated by an oscillator (not shown in the figure)  
provided in the clock generating unit 22b and has a  
15 frequency N times the frequency of the pixel clock clkwl.  
Thus, it is possible to arrange the scan start position  
of each scanning line on the photoconductor 11 at the  
same position. Additionally, upon detection of the  
synchronization detection signal detp input from the  
20 synchronization detection section 15, the clock  
generating unit 22b outputs a clear signal xlclr1 to the  
pulse train generating unit 21b.

The pulse train generating unit 21a generates  
an external pulse train (hereinafter may be simply  
25 referred to as "pulse") xpls0, which is a control signal

(control pulse signal) for applying a phase change at a desired timing with respect to the pixel clock `clkw0` generated by the clock generating unit 22a, and outputs the pulse `xpls0` to the clock generating unit 22a.

5           More specifically, the pulse train generating unit 21a starts a counting operation of the pixel clock `clkw0` upon an input of the clear signal `xlclr0`, and outputs the external pulse train `xpls0` to the clock generating unit 22a when a count value thereof reaches a  
10   predetermined setting value `prd0` (`prd0` indicates an interval of generation of the external pulse train `xpls0`). Thus, the pulse train generating unit 21a is capable of changing a phase of the pixel clock `clkw0` at the timing of outputting the external pulse train `xpls0`.  
15   The pulse train generating unit 21a stops the generation of the external pulse train `xpls0` when a number of the output external pulse train `xpls0` reaches the a predetermined setting value `num0` (`num0` indicates the number of pulses of the external pulse train `xpls0` and  
20   is represented by a positive integer).

          The pulse train generating unit 21b generates an external pulse train (hereinafter may be simply referred to as "pulse") `xpls1`, which is a control signal (control pulse signal) for applying a phase change at a  
25   desired timing with respect to the pixel clock `clkw1`

generated by the clock generating unit 22b, and outputs the pulse xpls1 to the clock generating unit 22b.

More specifically, the pulse train generating unit 21b starts a counting operation of the pixel clock clkw0 upon an input of the clear signal xlclr1, and outputs the external pulse train xpls0 to the clock generating unit 22b when a count value thereof reaches a predetermined setting value prd1 (prd1 indicates an interval of generation of the external pulse train xpls1). Thus, the pulse train generating unit 21b is capable of changing a phase of the pixel clock clkw1 at the timing of outputting the external pulse train xpls1. The pulse train generating unit 21b stops the generation of the external pulse train xpls1 when a number of the output external pulse train xpls1 reaches the a predetermined setting value num1 (num1 indicates the number of pulses of the external pulse train xpls1 and is represented by a positive integer).

The image data processing unit 23 applies image processing to the input image data by using various sets of information (information regarding a half-tone process, information for designating an image area based on a print paper size) used for image formation input from the register 24. Moreover, the image data processing unit 23 outputs the image signal

input from the printer controller 40 to the laser light source driver 14a in synchronization with the pixel clock clkw0. Further, the image data processing unit 23 outputs the image signal input from the printer  
5 controller 40 to the laser light source driver 14b in synchronization with the pixel clock clkwl.

The operation unit 50 serving as an input means is used for inputting information, and can be a group of key switches such as a touch panel or a  
10 keyboard. The operation unit 50 inputs the setting values prd0, prdl, num0 and numl.

The CPU 30 is constituted by a microcomputer which comprises a central processing unit, a program ROM (read only memory), etc., and generally controls the  
15 engine unit (the image forming apparatus) including the optical scanning apparatus 10 and the data control apparatus 20. The CPU 30 serves as scanning time comparing means and setting value calculating means. The CPU 30 outputs and sets the information input from  
20 the operation unit 50 to the register 24. Specifically, an operator of the image forming apparatus inputs the pulse generation intervals (periods) prd0 and prdl of the external pulse trains xpls0 and xpls1, and pulse generation numbers num0 and numl of the external pulse  
25 trains xpls0 and xpls1 by using the input keys of the



operation unit 50, etc. The CPU 30 sets the input  
setting values prd0, prd1, num0 and num1 to the register  
24. The CPU 30 outputs the phase delay control signal  
phase0p for delaying the phase of the pixel clock clkw0  
5 and a phase progress control signal phase0m to the  
resister 24 base on the external pulse train xpls0  
output from the pulse train generating unit 21a.  
Additionally, the CPU 30 outputs the phase delay control  
signal phaselp for delaying the phase of the pixel clock  
10 clkwl and a phase progress control signal phaselm to the  
resister 24 based on the external pulse train xpls1  
output from the pulse train generating unit 21a.

The register 24 serves as a storing medium for  
temporarily storing the setting values prd0, prd1, num0  
15 and num1 set by the CPU 30, and outputs the setting  
values prd0 and num0 to the pulse train generating unit  
21a and outputs the setting values prd1 and num1 to the  
pulse train generating unit 21b. Additionally, the  
register 24 outputs the phase delay control signal  
20 phase0p and the phase progress control signal phase0m  
input by the CPU 30 to the pulse train generating unit  
21a, and also outputs the phase delay control signal  
phaselp and the phase progress control signal phaselm  
input by the CPU 30 to the pulse train generating unit  
25 21b. Further, the register 24 outputs various sets of

information (information regarding a half-tone process, information for designating an image area based on a print paper size) used for image formation input by the CPU 30 to the image data processing unit 23.

5           The printer controller 40 sends the image data corresponding to a signal page to the image data processing unit as an image signal (video signal) on an individual line (scan line) basis.

          A description will now be given, with  
10   reference to FIGS. 7A and 7B, of a positional relationship between the laser light sources LD0 and LD1. FIG. 7A is an illustration showing a positional relationship between the laser light sources LD0 and LD1 in the first embodiment of the present invention. FIG.  
15   7B is an illustration for explaining the laser beam irradiation by the laser light sources LD0 and LD1 in the first embodiment of the present invention.

          In the present embodiment, as shown in FIG. 7A, the laser light sources LD0 and LD1 are arranged  
20   relative to each other with a distance  $W_x$  in the main-scanning direction and a distance  $W_y$  in the sub-scanning direction. Even if a plurality of laser light sources must be arranged with a predetermined distance due to a limitation in design, the laser beams can be irradiated  
25   with a desired line pitch (an interval of laser beams in

the sub-scanning direction) so as to form an image by the laser beams by arranging the plurality of laser light sources with a certain distance in the main-scanning direction as shown in FIG. 7A.

5                   When the two laser light sources LD0 and LD1 are arranged at the interval  $W_x$  in the main-scanning direction as shown in FIG. 7A, there is generated a difference between the irradiated positions on the polygon mirror 13 by the two laser light sources LD0 and  
10 LD1 as shown in FIG. 7B. Accordingly, if the laser light sources LD0 and LD1 project the laser beams at the same timing, the laser beam from the light source LD0 always incident on the synchronization detection unit 15 before the laser beam from the laser light source LD1.

15                   A description will now be given, with reference to FIG. 8, of an image forming operation performed by the image forming apparatus according to the present embodiment. FIG. 8 is a flowchart of an image forming operation performed by the image forming  
20 apparatus according to the first embodiment of the present invention.

                  First, the CPU 30 sets the setting values  $prd0$ ,  $prd1$ ,  $num0$  and  $num1$  input by the operation unit 50 to the register 24 (step S1). The register 24 outputs the  
25 corresponding setting values to the pulse train

generating units 21a and 21b.

When a start request of the image forming operation is input by the operation unit 50 (Yes of step S2), that is, for example, if a start key provided in  
5 the operation unit 50 is selected, the image forming apparatus starts the image forming operation.

The clock generating units 22a and 22b generate the pixel clocks clkw0 and clkwl based on the basic clocks clko0 and clko1, respectively. The clock  
10 generating unit 22a outputs the generated pixel clock clkw0 to the pulse train generating unit 21a and the image data processing unit 23. Additionally, the clock generating unit 22b outputs the generated pixel clock clkwl to the pulse train generating unit 21b and the  
15 image data processing unit 23 (step S3).

The image data processing unit 23 outputs the image signal input from the printer controller 40 to the laser light source drivers 14a and 14b in  
synchronization with the input pixel clocks clkw0 and  
20 clkwl, respectively (step S4).

The laser light source drivers 14a and 14b output drive control signals for controlling ON/OFF of illumination of the laser light sources LD0 and LD1, respectively, in accordance with the input timing of the  
25 image signal from the image data processing unit 23

based on the pixel clocks after the phase change and the contents of data of the image signal.

The laser light sources LD0 and LD1 project laser beams to the polygon mirror 13 based on the control by the laser light source drivers 14a and 14b, respectively (step S6). It should be noted that a lens (cylindrical lens) for condensing the laser beams may be provided between the laser light sources LD0 and LD1 and the polygon mirror 13.

The laser beam projected from the laser light sources LD0 and LD1 are deflected by the polygon mirror 13, transmit through the  $f\theta$  lens 12 and are incident on the synchronization detection unit 15, and, thereafter, the laser beams are incident on the surface of the photoconductor 11 to be scanned. When the synchronization detection unit 15 detects the laser beams (Yes of step S7), the synchronization detection unit 15 outputs the synchronization detection signal detp to the clock generating units 22a and 22b (step S8). As mentioned above in the present embodiment, since the laser beam from the laser light source LD0 is incident on the synchronization detection unit 15 always before the laser beam from the laser light source LD1, the synchronization detection unit 15 outputs the synchronous detection signal detp to the clock

generating unit 22a at the time of the first detection of the laser beams and also outputs the synchronization detection signal detp to the clock generating unit 22b at the time of the second detection of the laser beams.

5           If the synchronous detection signal detp is input, the clock generating units 22a and 22b generate the clear signals xlclr0 and xlclr1, and outputs them to the pulse train generating units 21a and 21b, respectively (step S9).

10           Upon reception of the clear signals xlclr0 and xlclr1, the pulse train generating units 21a and 21b start the count of the pixel clocks clkw0 and clkw1, respectively. The pulse train generating units 21a and 21b output the external pulse trains xpls0 and xpls1 to  
15 the clock generation sections 22a and 22b when the count values of the pixel clocks reach the setting values prd0 and prd1, respectively. The pulse train generating units 21a and 21b repeat the generation and output of the external pulse trains until the count values reach  
20 settings num0 and num1, respectively (step S10).

          When the external pulse trains xpls0 and xpls1 are input, the clock generating units 22a and 22b applies a phase change (delay/progress) to the pixel clocks clkw0 and clkw1 at the input timing (step S11).

25   It should be noted that the phase change can be

performed as a partial phase change, which can change a phase at a high level or a low level of each pixel clock by a time unit that is smaller than one period (hereinafter, referred to as "pixel clock period") of the pixel clock.

The clock generating unit 22a outputs the pixel clock clkw0, which was subjected to the phase change, to the pulse train generating unit 21a and the image data processing unit 23. Additionally, the clock generating unit 22b outputs the pixel clock clkw1, which was subjected to the phase change, to the pulse train generating unit 21b and the image data processing unit 23.

Thereafter, the image data processing unit 23 sends the image signal from the printer controller 40 to the laser light source drivers 14a and 14b in synchronization with the pixel clocks after the phase change. The laser light source drivers 14a and 14b perform a luminescence control of the laser light sources LD0 and LD1 according to the input timing of the image signal based on the pixel clocks after the phase change. The above-mentioned operation is repeated until a stop command of the image formation operation is supplied by the CPU 30 (No of step S12).

A description will now be given, with

reference to FIG. 9, of a relationship between the pixel clock and the phase change (phase setting).

FIG. 9 is a timing chart showing an example of the relationship between the pixel clock and the phase change thereof.

The clock generating unit 22a generates the pixel clock  $clkw0$  by using the reference clock  $clko0$ , which is M times (four times in FIG. 9) the frequency of the pixel clock  $clkw0$ , and outputs the pixel clock  $clkw0$  to the pulse generating unit 21a and the image data processing unit 23 in synchronization with the synchronization signal detection signal  $detp$  supplied by the synchronization detection unit 15. The clock generating unit 22a generates the pixel clock  $clkw0$  by toggling a high level (H) and a low level (L) of a reference clock (original clock)  $clko0$ , which is generated by an oscillator (not shown in the figure) provided in the clock generating unit 22a and has the frequency M times (four times in the example of FIG. 9) the frequency of the pixel clock  $clkw0$  at each  $MXclko0$  according to a count control.

The pulse train generating units 21a and 21b perform the phase control using the external pulse trains  $xpls0$  and  $xpls1$  so as to achieve the phase change, which shifts the phase of the pixel clocks  $clkw0$  and



clkwl, respectively.

The pulse train generating unit 21a outputs either the external pulse train xpls0p for delaying the phase angle of the pixel clock clkw0 or the external pulse train xpls0m for progressing the phase angle of the pixel clock clkw0, as an external pulse train xpls0. On the other hand, the pulse train generating unit 21b outputs either the external pulse train xpls1p for delaying the phase angle of the pixel clock clkwl or the external pulse train xpls1m for progressing the phase angle of the pixel clock clkwl, as an external pulse train xpls1.

For example, when generating the pixel clock clkw0 from the reference clock clko0, the pixel clock clkw, which is normally generated with 8clko, is generated with 9clko or 7clko by increasing or decreasing the count value i by inputting the external pulse train xpls0 (external pulse train xpls0p or xpls0m). That is, the pulse train generating unit 21a can shift the phase of the pixel clock clkw0 after the phase change by changing the phase by increasing the count value i while outputting the external pulse train xpls0m to the clock generating unit 22a. When considering one scan line in the main-scanning direction, the above-mentioned approach provides an effect that an

entire magnification is increased with  $T_m - 7/8$  (progress control), where  $T_m$  is a time of an entire scan line. On the other hand, if the pulse train generating unit 21a outputs the external pulse train  $xpls0p$  to the clock generating unit 22a and changes the phase by decreasing the count value  $i$ , the frequency of the pixel clock  $clkw0$  is increased to  $8/9$  times (delay control), which achieves a shift of the pixel clock  $clkw0$  after the phase change. When considering one scan line in the main-scanning direction, the above-mentioned approach provides an effect that an entire magnification is decreased with  $T_m + 7/8$  (delay control). Thus, the optical scanning apparatus 10 does not depend on an environmental fluctuation, and the image forming apparatus is capable of forming an image accurately on a desired position on the photoconductor.

It should be noted that although the relationship between the reference clock  $clko0$ , the pixel clock  $clkw0$  and the external pulse train  $xpls0$  and the phase change of the pixel clock  $clkol$  have been explained with reference to FIG. 9, the relationship between the reference clock  $clkol$ , the pixel clock  $clkwl$  and the external pulse train  $xpls1$  and the phase change of the pixel clock  $clkwl$  are the same and description thereof will be omitted.

A description will now be given, with reference to FIG. 10, of structures of the pulse train generating units 21a and 21b. FIG. 10 is a block diagram of the pulse train generating units 21a and 21b according to the first embodiment of the present invention.

First, the pulse train generating unit 21a will be described. The pulse train generating unit 21a comprises comparators 101 and 102, counters 103 and 104, and AND circuits 105 and 106.

The counter 103 inputs the clear signal  $xlclr0$  produced by the clock generating unit 22a from the synchronization detection signal  $detp$ , counts the number of pulses of the pixel clocks  $clkw0$  similarly input from the clock generating unit 22a on the basis of the input time, and outputs the count value  $i$  to the comparator 101.

The setting value  $prd0$  is input to the comparator 101 from the register 24, and is retained in the comparator 101. The comparator 101 compares the setting value  $prd0$  with the count value  $i$  from the counter 103, and generates and outputs the external pulse train  $xpls0$  when the count value  $i$  reaches the setting value  $prd0$  (or when the count value  $i$  becomes greater than the setting value  $prd0$ ).

The counter 104 receives the external pulse train xpls0 output from the comparator 101, counts the number of times of inputs (number of times of generations of the external pulse train xpls0), and  
5 outputs the count value j to the comparator 102.

The setting value num0 is input to the comparator 102 from the register 24, and is retained in the comparator 102. The comparator 102 compares the setting value num0 with the count value j from the  
10 counter 104, and generates and outputs the stop signal 0 for stopping the counting operation of the counter 103 when the count value j reaches the setting value num0 (or when the count value j becomes greater than the setting value num0).

15 The pulse xpls0 is input to the AND circuit 105 from the comparator 101. If the phase delay control signal phase0p is supplied from the register 24 at this time, the AND circuit 105 outputs the input pulse xpls0 to the clock generating unit 22a as a pulse xpls0p for  
20 the phase delay control.

The pulse xpls0 is input to the AND circuit 106 from the comparator 101. If the phase delay control signal phase0m is supplied from the register 24 at this time, the AND circuit 106 outputs the input pulse xpls0  
25 to the clock generating unit 22a as a pulse xpls0m for

the phase progress control.

Next, the pulse train generating unit 21b will be described. The pulse train generating unit 21b comprises comparators 111 and 112, counters 113 and 114, and AND circuits 115 and 116.

The counter 113 inputs the clear signal  $xlclr1$  produced by the clock generating unit 22b from the synchronization detection signal  $detp$ , counts the number of pulses of the pixel clocks  $clkwl$  similarly input from the clock generating unit 22b on the basis of the input time, and outputs the count value  $m$  to the comparator 111.

The setting value  $prd1$  is input to the comparator 111 from the register 24, and is retained in the comparator 111. The comparator 111 compares the setting value  $prd1$  with the count value  $m$  from the counter 113, and generates and outputs the external pulse train  $xpls1$  when the count value  $m$  reaches the setting value  $prd1$  (or when the count value  $m$  becomes greater than the setting value  $prd1$ ).

The counter 114 receives the external pulse train  $xpls0$  output from the comparator 111, counts the number of times of inputs (number of times of generations of the external pulse train  $xpls1$ ), and outputs the count value  $n$  to the comparator 112.

The setting value num1 is input to the comparator 112 from the register 24, and is retained in the comparator 112. The comparator 102 compares the setting value num1 with the count value n from the counter 114, and generates and outputs the stop signal 1 for stopping the counting operation of the counter 113 when the count value n reaches the setting value num1 (or when the count value n becomes greater than the setting value num1).

10           The pulse xpls1 is input to the AND circuit 115 from the comparator 111. If the phase delay control signal phase0p is supplied from the register 24 at this time, the AND circuit 115 outputs the input pulse xpls1 to the clock generating unit 22b as a pulse xpls1p for  
15 the phase delay control.

          The pulse xpls1 is input to the AND circuit 116 from the comparator 111. If the phase delay control signal phaselm is supplied from the register 24 at this time, the AND circuit 116 outputs the input pulse xpls1  
20 to the clock generating unit 22b as a pulse xpls1m for the phase progress control.

A description will now be given, with reference to FIG. 9 and FIG. 11, of an operation to generate the external pulse trains xpls0 and xpls1 by  
25 the pulse train generating units 21a and 21b according

to the present embodiment. FIG. 11 is a flowchart of operations of the pulse train generating units 21a and 21b according to the first embodiment of the present invention.

5                   First, the counters 103 and 104 reset the count values i and j to "1", respectively, when a power is supplied to the pulse train generating unit 21a (step S101).

                  Thereafter, the counter 103 waits for an input  
10   the clear signal xlclr0 (No of step S102), and after the clear signal xlclr0 is input (Yes of step S102), the counter 103 counts up or increments (+1) the count value i by 1 each time the pixel clock clkw0 is input (step S103).

15                   The comparator 101 performs the process of step S103 until the count value i reaches the setting value prd0 (No of step S104).

                  The comparator 101 generates the pulse xpls0 when the count value i reaches the setting value prd0  
20   (or when the count value i becomes greater than the setting value prd0). The counter 103 returns the count value i to "1" upon input of the pulse xpls0 (step S105). The pulse xpls0 generated by the comparator 101 is supplied to the AND circuits 105 and 106. At this time,  
25   when setting the pulse xpls0 as xpls0p for a phase delay

control, the phase delay control signal phase0p is supplied to the AND circuit 105. On the other hand, when setting the pulse xpls0 as xpls0m for a phase progress control, the phase progress control signal  
5 phase0m is supplied to the AND circuit 106. The AND circuit 105 outputs the pulse xpls0p for the phase delay control to the clock generating unit 22a if the phase delay control signal phase0p is input when the pulse xpls0 is supplied. The AND circuit 106 outputs the  
10 pulse xpls0m for the phase progress control to the clock generating unit 22b if the phase progress control signal phase0m is input when the pulse xpls0 is supplied.

As a result of comparison of the comparator 102 comparing the count value j of the counter 104 with  
15 the setting value num0, if the count value j has not reached the setting value num0 or the count value j is smaller than the setting value num0 (No of step S106), the counter 104 counts up or increments (+1) the count value j when the pulse xpls0 is input (step S107).

20           Thereafter, the counters 103 and 104 and the comparator 101 repeat the above-mentioned operations, and if the count value j reaches the setting value num0 (Yes of step S106), the comparator 102 generates the stop signal 0 and outputs the stop signal 0 to the  
25 counter 103. When the stop signal 0 is supplied to the



counter 103, the counter 103 stops the count operation.

Next, the counters 113 and 114 reset the count values m and n to "1", respectively, when a power is supplied to the pulse train generating unit 21b (step  
5 S108).

Thereafter, the counter 113 waits for an input the clear signal xlclr1 (No of step S109), and after the clear signal xlclr1 is input (Yes of step S109), the counter 113 counts up or increments (+1) the count value  
10 m by 1 each time the pixel clock clkwl is input (step S110).

The comparator 111 performs the process of step S113 until the count value m reaches the setting value prd1 (No of step S111).

15 The comparator 111 generates the pulse xpls1 when the count value m reaches the setting value prd1 or when the count value m becomes greater than the setting value prd1 (Yes of step S111). The counter 113 returns the count value m to "1" upon input of the pulse xpls1  
20 (step S112).

As a result of comparison of the comparator 112 comparing the count value n of the counter 104 with the setting value num1, if the count value n has not reached the setting value num1 or the count value n is  
25 smaller than the setting value num1 (No of step S113),

the counter 114 counts up or increments (+1) the count value n when the pulse xpls1 is input (step S114).

Thereafter, the counters 113 and 114 and the comparator 111 repeat the above-mentioned operations,  
5 and if the count value n reaches the setting value num1 (Yes of step S113), the comparator 112 generates the stop signal 1 and outputs the stop signal 1 to the counter 113. When the stop signal 1 is supplied to the counter 113, the counter 113 stops the count operation.

10 It should be noted that besides the above-mentioned method, there is a method of generating a fixed pulse train using a random access memory (RAM) table to output data by counting addresses with the pixel clocks clkw0 and clkw1.

15 Additionally, although the pulse train generating unit 21b starts the operation of generating the external pulse train xpls1 after the pulse train generating unit 21a ended the operation of generating the external pulse train xpls0 in the example of FIG. 11,  
20 the operations of the pulse train generating units 21a and 21b can be performed concurrently.

FIG. 12 is a timing chart showing a relationship between the clear signal xlclr0 and the external pulse train xpls0 according to the first  
25 embodiment of the present invention.

As shown in FIG. 12, the pulse train generating unit 21a starts the output of the external pulse train xpls0 after the setting value prd0 has passed after the input of the clear signal xlclr0. At this time, the pulse train generating unit 21a outputs the external pulse train xpls0 having a pulse width of 1clkw0 until an input of a following external pulse train xpls0 at a period prd0 with a number of pulses num0.

Although the image forming apparatus performs scanning using the two laser light sources LD0 and LD1 in the present embodiment, the number of laser is not limited to two and three or more laser light sources may be used. In such a case, a laser light source driver, a pulse train generating unit and a clock generating unit are provided for each laser light source so as to perform a phase change on an individual laser light source basis.

As explained above, according to the present embodiment, in the image forming apparatus using two or more laser light sources so as to perform image formation according to a multi-beam method, the pulse train generating unit and the clock generating unit are provided for each laser light source so as to perform the phase change of the laser beams on an individual

laser light source basis. Each pulse train generating unit and each clock generating unit perform the phase change of the pixel clock, which controls a projection timing of the laser beam of the laser light sources, respectively, based on the predetermined setting values (setting values indicating the period and the number of the phase changes). Therefore, even if the wavelengths of the laser beams projected from a plurality of laser light sources provided in the image forming apparatus are different from each other, a high-quality image can be formed on a medium to be scanned by using a common optical system.

(Second Embodiment)

15 In the first embodiment of the present invention, the synchronization detection unit 15, which aligns the scan start positions in the main scanning direction, outside the area of the surface of the photoconductor 11 to be scanned along the scanning paths of the laser beams in the main-scanning direction. In the second embodiment of the present invention, two synchronization detection units (a front-end synchronization detection unit 16 and a rear-end synchronization detection unit 17) are provided outside 25 the area of the surface of the photoconductor 11 to be

scanned along the scanning paths of the laser beams in the main-scanning direction. By measuring the time (the number of clocks) corresponding to a scan between the front-end synchronization detection unit 16 and the rear-end synchronization detection units 17, an error in the write magnification of the laser light sources LD0 and LD1 is measured.

A description will now be given, with reference to FIG. 13, of a structure of an image forming apparatus according to the second embodiment. FIG. 13 is a block diagram of the image forming apparatus according to the second embodiment of the present invention. It should be noted that, unless it is specifically mentioned below, the structure and operation of the image forming apparatus according to the present embodiment are the same as that of the first embodiment of the present invention.

As shown in FIG. 13, the image forming apparatus comprises an optical scanning apparatus 10, a data control apparatus 20, a CPU 30, a printer controller 40, and an operation unit 50 serving as input means. It should be noted the structure of the image forming apparatus shown in FIG. 13 is simplified, and the image forming apparatus may comprise parts other than the parts shown in FIG. 8.

The optical scanning apparatus 10 performs image formation by laser beams. The optical scanning apparatus comprises a photoconductor 11 serving as a medium to be scanned, an  $f\theta$  lens 12, a polygon mirror 13 serving as rotational deflection means, laser light source drivers 14a and 14b, the front-end synchronization detection unit 16 as synchronous detection means and a rear-end synchronization detection unit 17, and laser light sources LD0 and LD1.

10 The optical scanning apparatus 10 according to the present embodiment is provided with the front-end synchronization detection unit 16 and the rear-end synchronization detection unit 17 instead of the synchronization detection unit 15 in the first  
15 embodiment.

The front-end synchronization detection unit 16 is provided outside (immediately preceding the scan start position) the image area of the surface of the photoconductor 11 to be scanned along the paths of the  
20 laser beams in the main-scanning direction. Similar to the synchronization detection unit 15 in the first embodiment, the front-end synchronization detection unit 16 detects the laser beams transmitting through the  $f\theta$  lens 12 and irradiated thereon. Upon detection of the  
25 laser beams from the laser light sources LD0 and LD1,

the front-end synchronization detection unit 16 generates the synchronization detection signal detp, which specifies the write start positions of the laser beams in the main-scanning direction (for aligning the  
5 write start positions always at the same position on the surface to be scanned), and outputs the signal detp to the data control apparatus 20.

The rear-end synchronization detection unit 17 is provided outside (immediately proceeding the scan  
10 start position) the image area of the surface of the photoconductor 11 to be scanned along the paths of the laser beams in the main-scanning direction. The rear-end synchronization detection unit 17 detects the laser beams from the laser light source LD0 and LD1 after  
15 scanning of one scan period is completed. The rear-end synchronization detection unit 17 outputs, when detecting the laser beams, a scan end signals edp0 and edp1, which indicate the completion of the scan corresponding to one scanning period (one scan line), to  
20 scanning time measuring units 25a and 25b.

It is assumed that other parts provided in the optical scanning apparatus 10 have the same structures as the first embodiment, and performs the same operations.

25 The data control apparatus 20 outputs the

image signal for controlling the laser light source drivers 14a and 14b so as to control the laser beam write operation performed by the optical scanning apparatus 10. The data control apparatus 20 comprises

5 pulse train generating units 21a and 21b serving as scan time measuring means, clock generating units 22a and 22b serving as pixel clock generating means, an image data processing unit 23, a register 24, and the scan time measuring units 25a and 25b serving as scan time

10 measuring means.

The data control apparatus 20 according to the second embodiment has the same structure as the data control apparatus 20 according to the first embodiment except for the scan time measuring units 25a and 25b

15 added thereto.

Similar to the first embodiment, the clock generating unit 22a outputs the pixel clock clkw0 and the clear signal xlclr0 to the pulse train generating unit 21a, and also outputs the pixel clock clkw0 and the

20 clear signal xlclr0 to the scan time measuring unit 25a.

The clock generating unit 22b outputs the pixel clock clkw1 and the clear signal xlclr1 to the pulse train generating unit 21b, and also outputs the pixel clock clkw1 and the clear signal xlclr1 to the

25 scan time measuring unit 25b.



The pixel clock clkw0 and the clear signal xlclr0 are supplied to the scan time test measuring unit 25a from the clock generating unit 22a. Additionally, the scan end signal dep0 is supplied to the scan time measuring unit 25a from the rear-end synchronization detection unit 17. The scan time measuring unit 25a measures the time (the number of pulses of the pixel clock) T0 (measured value T0: T0 is a positive integer) after the clear signal xlclr0 is input until the scan end signal edp0 is input, and outputs the measure value T0 to the register 24.

The pixel clock clkw1 and the clear signal xlclr1 are input to the scan time measuring unit 25b from the clock generating unit 22b. Additionally, the scan end signal dep1 is supplied to the scan time measuring unit 25b from the rear-end synchronization detection unit 17. The scan time measuring unit 25b measures the time (the number of pulses of the pixel clock) T1 (measured value T1: T1 is a positive integer) after the clear signal xlclr1 is input until the scan end signal edp1 is input, and outputs the measure value T1 to the register 24.

The register 24 serves as a memory medium temporarily storing, in addition to the setting values prd0, prd1, num0 and num1 set by the CPU 30, the

measured values T0 and T1 supplied from the respective scan time measuring unit 25a and 25b. Additionally, the register 24 retains a reference value Tref, which indicates a time period after the clear signal xlclr0 is  
5 input until the scan end signal edp0 is input in a state where there is no error in the write magnification. The reference value Tref is a positive integer indicating a predetermined time period (number of clock pulses). The register 24 outputs the setting values prd0 and num0 to  
10 the pulse train generating unit 21a, and outputs the setting values prd1 and num1 to the pulse train generating unit 21b.

The CPU 30 is a microcomputer, which comprises a central processing unit, a program ROM, etc., and  
15 generally controls an entire engine unit containing the optical scanning apparatus 10 and the data control apparatus 20. The CPU 30 serves as scan time comparison means and setting value computation means. Similar to the first embodiment, the CPU 30 sets the setting values  
20 prd0, prd1, num0 and num1 input through the operation unit 50 to the register 24. In the present embodiment, the CPU 30 further computes a difference between the write magnifications of the laser light sources LD0 and LD1 using the reference value Tref and measured values  
25 T0 and T1 retained in the register 24. Based on the

difference between the write magnifications, the CPU 30  
computes new setting values prd0, prd1, num0 and num1,  
and sets them in the register 24. The pulse train  
generating unit 21a newly generates the external pulse  
5 train xpls0 based on the setting values prd0 and num0  
newly set in the register 24. Similarly, the pulse  
train generating unit 21b newly generates the external  
pulse train xpls1 based on the setting values prd1 and  
num1 newly set in the register 24. Thus, according to  
10 the present embodiment, the time period after the laser  
beams are incident on the front-end synchronization  
detection unit 16 until the laser beams are incident on  
the rear-end synchronization detection unit 17 is  
measured, the differences between the reference value  
15 Tref and each of the measured values T0 and T1 are  
computed, and a number of pulses of the external pulse  
train to be generated is determined based on the  
computed differences. Therefore, the write  
magnification difference caused by a plurality of laser  
20 light sources can be automatically corrected, which  
enables an easy control of a deterioration of an image  
caused by the write magnification difference.

A description will now be given, with  
reference to FIGS. 14, 15A and 15B, of an operation of  
25 measuring the measured value T0 and T1 of the laser

light sources LD0 and LD1 by the scan time measuring units 25a and 25b. FIG. 14 is a time chart showing the signals output from the front-end synchronization detection unit 16 and the rear-end synchronization detection unit 17 according to the second embodiment of the present invention. FIG. 15A is an illustration showing a positional relationship between the laser light sources LD0 and LD1 according to the second embodiment of the present invention. FIG. 15B is an illustration showing the laser beam irradiation by the laser light sources LD0 and LD1 according to the second embodiment of the present invention.

As shown in FIG. 14, the front-end synchronization detection unit 16 and the rear-end synchronization detection unit 17 detect incidence of the laser beams projected from the laser light sources LD0 and LD1. At this time, the front-end synchronization detection unit 16 and the rear-end synchronization detection unit 17 detect the laser beam from the laser light source LD1 after the detection of the laser beam from the laser light source LD0.

A description will be given of a structure in which the front-end synchronization detection unit 16 and the rear-end synchronization detection unit 17 always detect the laser beam from the laser light source

D0 prior to the laser beam from the laser light source D1.

As shown in FIGS. 15A and 15B, the laser light source LD0 is located at a distance  $W_x$  apart from the laser light source LD1 in the main-scanning direction. Using the distance  $W_x$ , positions on the polygon mirror 13 on which the laser beams are incident are shifted from each other. That is, the laser beam from the laser light source LD0 is caused to be incident on a position on the upstream side of a position on which the laser beam from the laser light source LD1 is incident in a rotating direction of the polygon mirror 13. Thus, the laser beam from the laser light source LD0 is caused to always be incident on the front-end synchronization detection unit 16 and the rear-end synchronization detection unit 17 at an earlier timing than the laser beam from the laser light source LD1.

Moreover, it is also possible to cause the laser beam from the laser light source LD0 always be incident on the front-end synchronization detection unit 16 and the rear-end synchronization detection unit 17 at an earlier timing than the laser beam from the laser light source LD1 by controlling the laser light sources LD0 and LD1 so that the laser light source D0 always projects the laser beam earlier than the laser light

source LD1. A description will be given below of such an operation.

First, the laser light source LD0 projects a laser beam. Upon detection of the incidence of the laser beam (from the laser light source LD0), the front-end synchronization detection unit 16 outputs a signal, which indicates that the laser beam from the laser light source LD0 is incident, to the laser light source driver 14b. Upon reception and recognition of the signal indicating the incidence of the laser beam from the laser light source LD0, the laser light source driver 14b starts projection of the laser beam of the laser light source LD1. Thus, since laser light source LD1 projects the laser beam after the laser beam from the LD0 is detected by the front-end synchronization detection unit 16, it becomes possible to always cause the laser beam from the laser light source LD0 always be incident on the front-end synchronization detection unit 16 and the rear-end synchronization detection unit 17 at an earlier timing than the laser beam from the laser light source LD1.

The image forming apparatus may have one or both of the above-mentioned two mechanisms (the adjustment of the incidence position to the polygon mirror 13 and the adjustment of the projection timing of

the laser beams).

A description will now be given, with reference to FIG. 16, of a structure of the scan time measuring units 25a and 25b. FIG. 16 is a block diagram of the scan time measuring units 25a and 25b according to the second embodiment of the present invention.

The scan time measuring unit 25a comprises a counter 201 and a latch 202. The pixel clock clkw0 and the clear signal xlclr0 are supplied to the counter 201 from the clock generating unit 22a. The scan end signal edp0 is supplied to the latch 202 from the rear-end synchronization detection unit 17. The counter 201 starts a count of the pixel clock clkw0 on the basis of the time of the clear signal xlclr0 being supplied thereto. The latch 202 latches the count value (the number of pulses of the pixel clock) of the counter 201 at the input time when the scan end signal edp0 is supplied thereto. The latch 202 outputs the count value as the measured value (time) T0 to the register 24. The count value corresponds to a number of pulses of the pixel clock from the time the clear signal xlclr0 is input to the counter 201 to the time the scan end signal edp0 is input to the latch 202.

The scan time measuring unit 25b comprises a counter 211 and a latch 212. The pixel clock clkwl and

the clear signal xlclr1 are supplied to the counter 211 from the clock generating unit 22b. The scan end signal edp1 is supplied to the latch 212 from the rear-end synchronization detection unit 17. The counter 211  
5 starts a count of the pixel clock clkwl on the basis of the time of the clear signal xlclr1 being supplied thereto. The latch 212 latches the count value (the number of pulses of the pixel clock) of the counter 211 at the input time when the scan end signal edp1 is  
10 supplied thereto. The Latch 212 outputs the count value as the measured value (time) T1 to the register 24. The count value corresponds to a number of pulses of the pixel clock from the time the clear signal xlclr1 is input to the counter 211 to the time the scan end signal  
15 edp1 is input to the latch 212.

A description will now be given, with reference to FIG. 17, of an operation to adjust the phase of the pixel clock clkw0 by the image forming apparatus according to the present embodiment. FIG. 17  
20 is a flowchart of the phase adjusting operation of the pixel clock by the image forming apparatus according to the second embodiment of the present invention.

First, the front-end synchronization detection unit 16 performs a detection operation until a laser  
25 beam is detected (No of step S201), and if a first laser



beam (the laser beam from the laser light source LD0) is detected (Yes of step S201), the front-end synchronization detection unit 16 outputs the synchronization detection signal detp to the clock generating unit 22a. The clock generating unit 22a generates the clear signal xlclr0 on the basis of the time of the synchronization detection signal detp being input thereto, and outputs the generated clear signal xlclr0 to the scan time measuring unit 25a.

10           The counter 201 of the scan time measuring unit 25a starts the count of the pixel clock clkw0 on the basis of the time of the clear signal xlclr0 being input thereto (step S202).

          The rear-end synchronization detection unit 17 performs a detection operation until a laser beam is detected (No of step S203), and if a first laser beam (the laser beam from the laser light source LD0) is detected (Yes of step S203), the rear-end synchronization detection unit 17 outputs the scan end signal detp0 to the scan time measuring unit 25a. The latch 202 of the scan time measuring unit 25a latches the count value of the counter 201 at the time when the scan end signal edp0 is supplied thereto (step S204). The count value latched at this time indicates the number of pulses of the pixel clock from the time when

15  
20  
25

the clear signal `xlclr0` is input to the counter 201 to the time when the scan end signal `edp0` is input to the latch 202, that is, the number of pulses of the pixel clock from the time when the laser beam of the laser light source LD0 is incident on the front-end synchronization detection unit 16 to the time when the laser beam of the laser light source LD0 is incident on the rear-end synchronization detection unit 17. The latched count value is retained in the register 24 as the measured value T0.

Next, the CPU 30 computes the number of pulses to be increased or decreased by the pulse train generating unit 21a by using the measured value T0, the reference value `Tref` and a phase unit retained in the register 24 (step S205). It should be noted that the phase unit is a minimum unit that is capable of increasing or decreasing a phase shift of the pixel clock, and is represented by  $(\text{frequency of pixel clock}) / (\text{frequency of basic clock})$ . For example, in the example shown in FIG. 9, one pixel clock `clkw0` includes eight basic clocks `clock0`. In this case, since the phase control can be performed by a unit of `1clk0`, that is, a unit of  $1/8$  clock, the phase unit is "1/8".

A description will now be given of a method of computing the number of the output pulses that is

increased or decreased by the pulse train generating unit 21a. The CPU 30 calculates (measured value T0 - reference value Tref)/(phase unit) so as to compute the number of pulsed to be increased or decreased. For  
5 example, if the measured value T0 is "8(clkw)", the reference value is "5(clkw)" and the phase unit is "1/8", the CPU computes as  $(8-5) \times 8 = 24$ .

The CPU 30 newly sets the setting values prd0 and num0 and writes them in the register 24 so that the  
10 pulse train generating unit 21a increases or decreases the number of the output pulses computed (step S206). For example, as mentioned above, since the computed value is positive if the computed value is "24", the CPU 30 newly sets the setting values prd0 and num0 (last  
15 num0 + computed value (24)) in the register 24 so that the number of output pulses is increased by "24", and outputs the phase progress control signal phase0m to the pulse train generating unit 21a. If the computed value is negative, the CPU 30 newly sets the setting values  
20 prd0 and num0 (last num0 + computed value (a negative integer) in the register 24 so that the number of output pulses is decreased by "the negative integer", and outputs the phase delay control signal phase0p to the pulse train generating unit 21a.

25 It should be noted that the CPU 30 newly sets

the setting values  $prd0$  and  $num0$ , which satisfy the condition " $xlclr0 \text{ interval} > prd0 \times num0$ " so that the number  $num$  of the output pulses are contained in the interval (one scan period) of the clear signal  $xlclr0$ .

5           The process shown in FIG. 17 may be repeated each time a laser beam is detected by the front-end synchronization detection unit 16 and the rear-end synchronization detection unit 17 (each time the measured value  $T0$  is generated). In such a case, it  
10 becomes possible to correct write errors caused by the laser light sources by adjusting the phase of the pixel clock on an individual main-scanning line basis.

          Although the phase change operation of the pixel clock  $clkw$  has been explained in the above  
15 descriptions, the phase change operation of the pixel clock  $clkwl$  can also be performed in the same manner. That is, the setting values  $prd1$  and  $num1$  are set after measuring the number of pixel clocks after the laser beam of the laser light source  $LD1$  is incident on the  
20 front-end synchronization detection unit 16 until the laser beam of the laser light source  $LD1$  is incident on the rear-end synchronization detection unit 17.

          Moreover, although description has been given in the present embodiment of the case where the image  
25 forming apparatus performs a scanning operation using

the two laser light sources LD0 and LD1, the number of laser light sources is not limited to two, and more than three laser light sources can be used to perform the scanning operation. In such a case, the image forming apparatus is provided with U scan time measuring units, U laser light source drivers, U pulse train generating units and U clock generating units, where U is an integer greater than two, so that each scan time measuring unit measures a time period from the time when a laser beam of the corresponding laser light source is incident on the front-end synchronization detection unit 16 until the laser beam is incident on the rear-end synchronization detection unit 17. The CPU 30 sets the setting values of each laser light source using the measured values.

As explained above, according to the present embodiment, the measured values T0 and T1 (numbers of pixel clocks) from the time when the laser beams of the laser light sources LD0 and LD1 are detected by the front-end synchronization detection unit 16 until the laser beams are detected by the rear-end synchronization detection unit 17 so as to compute the number of pulses of the pulse xpls0 and xpls1, which are generated and output by the pulse train generating units 21a and 21b, to be increased or decreased in accordance with the

measured values T0 and T1. The pulse train generating units 21a and 21b output the external pulse trains xpls0 and xpls1 based on the number of the pulses to be increased or decreased, respectively. Therefore, an operation of an operator to input the setting values prd0, prd1, num0 and num1 can be omitted, and it is possible to easily correct the write magnification difference, which is caused by a difference in wavelength between more than two laser light sources (laser light sources LD0 and LD1). Moreover, even in a case where a write error of the laser light sources occurs due to an environmental fluctuation with time such as a temperature change during operation of the image forming apparatus, the correction of the write error can be performed on an individual scan line basis, which enables formation of an accurate image.

(Third Embodiment)

In the first embodiment of the present invention, the setting values (setting values prd0, prd1, num0, and num1) are input for each laser light source. On the other hand, in the present embodiment, it is possible to easily correct a write error of each laser light source, even in a case where the image forming apparatus has more than two laser light sources, by

merely inputting setting values (an interval of the external pulse train and a number of pulses to be generated) to only one of the laser light sources.

5 A description will be given below of a structure and an operation of the image forming apparatus according to the present embodiment.

The image forming apparatus according to the present embodiment performs image formation using more than two laser light sources and sharing one optical system. If a write error due to more than two laser light sources is caused by a distortion of a lens in an optical system that is common to the laser light sources, a write magnification difference between more than two laser light sources, that is, the relative reference in 15 the setting values (an interval of the external pulse train and a number of pulses to be generated) does not change due to environmental fluctuations. In such a case, the image forming apparatus is capable of correcting the write error difference of all of the 20 laser light sources by merely inputting the setting values with respect to only one of the laser light sources by storing information indicating relative differences between the setting values of the laser light sources.

25 FIG. 18 is a block diagram of the image

forming apparatus according to the third embodiment of the present invention. It should be noted that the structure and operation of the image forming apparatus according to the present embodiment are the same as that of the image forming apparatus according to the above-mentioned first embodiment except for the parts specifically described below.

As shown in FIG. 18, the image forming apparatus comprises an optical scanning apparatus 10, a data control apparatus 20, a CPU 30 serving as scan time comparison means or setting value computation means, a printer controller 40, and an operation unit 50 serving as input means. It should be noted that the structure of the image forming apparatus shown in FIG. 18 is simplified, and the image forming apparatus may have structural parts other than the parts shown in FIG. 18.

The optical scanning apparatus 10 uses laser beams to form an image, and comprises a photoconductor 11 serving as a medium to be scanned, an  $f\theta$  lens 12, a polygon mirror 13 serving as rotational deflection means, laser light source drivers 14a and 14b, a synchronization detection unit 15 serving as synchronization detection means, and laser light sources LD0 and LD1.

The data control apparatus 20 outputs an image



signal for controlling the laser light source drivers  
14a and 14b so as to control a laser beam write  
operation performed by the optical scanning apparatus 10.  
The data control apparatus 20 comprises pulse train  
5 generating units 21a and 21b serving as phase control  
means, clock generating units 22a and 22b serving as  
pixel clock generation means, an image data processing  
unit 23, and a register 24 serving as setting value  
retaining means.

10               The register 24 according to the present  
embodiment retains further setting values for the laser  
light source LD1 and difference setting values prd1d  
(setting value prd1 of LD1 - setting value prd0 of LD0)  
and num1d (setting value num1 of LD1 - setting value  
15 num0 of LD0). That is, the difference setting value  
prd1d corresponds to a difference in a pulse generation  
interval (pixel clock number) between the laser light  
source LD1 and the laser light source LD0, and the  
difference setting value num1d corresponds to a  
20 difference in a number of pulses between the laser light  
source LD1 and the laser light source LD0. It should be  
noted that the difference setting values prd1d and num1d  
are set to integers.

                  A description will now be given, with  
25 reference to FIGS. 18 through 20, of an operation of

setting the setting values of each laser light source in the image forming apparatus according to the third embodiment of the present invention. FIG. 19 is an illustration showing the setting operation of the setting values of the laser light sources LD0 and LD1 according to the third embodiment of the present invention. FIG. 20 is a flowchart of the setting operation of the setting values of the laser light sources LD0 and LD1 according to the third embodiment of the present invention.

First, the operation unit 50 supplies the setting value prd0 (an interval of generation of the external pulse train) of the laser light source LD0, and the setting value num0 (a number of pulses of the external pulse train to be generated) in accordance with an operation of an operator.

The CPU 30 determines whether or not the setting values prd0 and num0 of the laser light source LD0 are supplied (step S301). If it is determined that the setting values prd0 and num0 have not been supplied (No of step S301), the operation of step S301 is repeated.

When the CPU 30 recognizes an input of the setting values prd0 and num0 (Yes of step S201), the CPU 30 reads the difference setting values prdld and numld

(step S302).

Then, the CPU 30 computes the setting value prd1 of the laser light source LD1 by adding the difference setting value prdd to the setting value prd0 of the laser light source LD0. Additionally, the CPU 30 computes the setting value num1 of the laser light source LD1 by adding the difference setting value numd of LD0 to the setting value num0 of the laser light source LD0 (step S303).

Although the image forming apparatus according to the present embodiment uses two laser light sources LD0 and LD1 to perform the scanning operation, the number of laser light sources is not limited to two and three or more laser light sources may be used to perform a scanning operation. In such a case, the image forming apparatus is provided with the laser light driver, the pulse train generating unit and the clock generating unit for each laser light source. Additionally, the register 24 retains the difference setting value with respect to one of the laser light sources for each of the laser light sources so that the CPU 30 sets the setting values to each of the laser light sources by using the difference setting values retained in the register 24.

As mentioned above, according to the present

embodiment, information (difference setting values)  
indicating a relative difference between each of the  
laser light sources and one reference laser light source  
is previously stored for each of the laser light sources,  
5 and if the setting values of the reference laser light  
source are input prior to a start of a laser beam  
scanning, the setting values of other laser light  
sources are computed and set in accordance with the  
previously stored difference setting values. Therefore,  
10 the setting value of other laser light sources are  
automatically set merely by setting the setting values  
of one of the laser light source, and the write  
magnification difference of each laser light source can  
be corrected easily.

15

(Fourth Embodiment)

An image forming apparatus according to a  
fourth embodiment of the present invention can be  
achieved by the image forming apparatus according to the  
20 second embodiment of the present invention, which is  
configured and arranged to be capable of performing the  
setting operation of the setting values that is  
performed by the image forming apparatus according to  
the third embodiment of the present invention.

25

A description will now be given, with

reference to FIG. 21, of a structure of the image forming apparatus according to the fourth embodiment of the present invention. FIG. 21 is a block diagram of the image forming apparatus according to the fourth  
5 embodiment of the present invention. It should be noted that the structure and operation of the image forming apparatus according to the present embodiment are the same as that of the image forming apparatus according to the second embodiment except for the parts specifically  
10 described below.

As shown in FIG. 21, the image forming apparatus comprises an optical scanning apparatus 10, a data control apparatus 20, a CPU 30, a printer controller 40, and an operation unit 50. It should be  
15 noted that the structure of the image forming apparatus shown in FIG. 21 is simplified, and the image forming apparatus may have structural parts other than the parts shown in FIG. 21.

The optical scanning apparatus 10 uses laser  
20 beams to form an image, and comprises a photoconductor 11 serving as a medium to be scanned, an  $f\theta$  lens 12, a polygon mirror 13 serving as rotational deflection means, laser light source drivers 14a and 14b, a front-end synchronization detection unit 16 and a rear-end  
25 synchronization detection unit 17 serving as

synchronization detection means, and laser light sources LD0 and LD1.

The data control apparatus 20 outputs an image signal for controlling the laser light source drivers 14a and 14b so as to control a laser beam write operation performed by the optical scanning apparatus 10. The data control apparatus 20 comprises pulse train generating units 21a and 21b serving as phase control means, clock generating units 22a and 22b serving as pixel clock generation means, an image data processing unit 23, a register 24, and a scan time measuring unit 25a serving as scan time measurement measuring means.

The register 24 according to the present embodiment retains, similar to the third embodiment, setting values for the laser light source LD1 and difference setting values prd1d (setting value prd1 of LD1 - setting value prd0 of LD0) and num1d (setting value num1 of LD1 - setting value num0 of LD0).

A description will now be given, with reference to FIGS. 22, of an operation of setting the setting values of the setting values ped0, prd1, num0 and num1 performed by the CPU 30 according to the present embodiment. FIG. 22 is a flowchart of the setting operation of the setting values performed by the image forming apparatus according to the third

embodiment of the present invention.

First, the CPU 30 newly sets the setting values prd0 and num0 of the laser light source LD0 in accordance with the measured value T0 that indicates the pixel clock number from the time when the laser beam of the laser light source LD0 is incident on the front-end synchronization detection signal 16 to the time when the laser beam of the laser light source is incident on the rear-end synchronization detection signal 17 (step S401). It should be noted that the process of step S401 can be the same as the process shown in FIG. 18.

Then, the CPU 30 computes the setting values prd1 and num1 of the laser light source LD1 in accordance with the newly set setting values prd0 and num0 of the laser light source LD0 and the difference setting values prd1d and num1d and the phase unit previously retained in the register 24, and writes the setting values prd1 and num 1 in the register 24 (No of step S403).

The CPU 30 newly computes the setting values prd0, prd1, num0 and num1 each time a new measured value T0 is input (Yes of step S403). If there is no input of a new measured value T0 (No of step S403), the setting operation of the setting values is ended.

Although the image forming apparatus according

to the present embodiment uses two laser light sources LD0 and LD1 to perform the scanning operation, the number of laser light sources is not limited to two and three or more laser light sources may be used to perform  
5 a scanning operation. In such as case, the image forming apparatus is provided with the laser light driver, the pulse train generating unit and the clock generating unit for each laser light source.

Additionally, the register 24 retains the difference  
10 setting value with respect to one of the laser light sources for each of the laser light sources so that the CPU 30 sets the setting values to each of the laser light sources by using the difference setting values retained in the register 24.

15 As explained above, according to the present embodiment, the measured value T0 (pixel clock number) from the time when the laser beams of the laser light source LD0 is detected by the front-end synchronization detection unit 16 until the laser beam is detected by  
20 the rear-end synchronization detection unit 17 is measured so as to set the setting values prd0 and dnum0 of the laser light source LD0 by using the measured value T0 and control the number of pulses of the pulse xpls0 output by the pulse train generating unit 21a.

25 Then, the number of pulses of the pulse xpls1,



which is generated and output by the pulse train  
generating units 21b, is computed in accordance with the  
difference setting values prd1d and num1d, the setting  
values prd0 and num0 of the laser light source LD0 and  
5 the phase unit previously retained in the register 24 so  
as to control the number of pulses of the pulse xplsl  
output by the pulse train generating unit 21b.

Therefore, an operation of an operator to  
input the setting values prd0, prd1, num0 and num1 can  
10 be omitted, and it is possible to easily correct the  
write magnification difference, which is caused by a  
difference in wavelength between more than two laser  
light sources (laser light sources LD0 and LD1).  
Moreover, even in a case where a write error of the  
15 laser light sources occurs due to an environmental  
fluctuation with time such as a temperature change  
during operation of the image forming apparatus, the  
correction of the write error can be performed on an  
individual scan line basis, which enables formation of  
20 an accurate image.

Moreover, the laser beam of only one of the  
laser light sources (laser light source LD0) is detected  
by the front-end synchronization detection unit 16 and  
the rear-end synchronization detection unit 17 so as to  
25 correct the write error, and write errors of other laser

light sources are corrected according to program processing using the difference setting values previously retained in the register 24. Therefore, only one scan time measuring unit is provided (that is, there is no need to provide a number of scan time measuring units corresponding to a number of laser light sources), which achieves an easy correcting process of write errors.

10 (Fifth Embodiment)

If a phase change of the pixel clock is repeatedly performed at the same position in the main-scanning direction, there may occur a case in which a highly visible pattern such as a line extending in the longitudinal direction (sub-scanning direction) is formed in an output image (final image). The image forming apparatus according to the fifth embodiment of the present invention prevents formation of the above-mentioned highly visible pattern by varying the position in the main-scanning direction at which the phase change of the pixel clock is performed.

A description will now be given, with reference to FIG. 23, of a structure of the image forming apparatus according to the fifth embodiment of the present invention. FIG. 23 is a block diagram of

the image forming apparatus according to the fifth embodiment of the present invention. It should be noted that the structure and operation of the image forming apparatus according to the present embodiment are the same as that of the image forming apparatus according to the first embodiment except for the parts specifically described below.

As shown in FIG. 23, the image forming apparatus comprises an optical scanning apparatus 10, a data control apparatus 20, a CPU 30, a printer controller 40, and an operation unit 50. It should be noted that the structure of the image forming apparatus shown in FIG. 23 is simplified, and the image forming apparatus may have structural parts other than the parts shown in FIG. 23.

The optical scanning apparatus 10 uses laser beams to form an image, and comprises a photoconductor 11 serving as a medium to be scanned, an  $f\theta$  lens 12, a polygon mirror 13 serving as rotational deflection means, laser light source drivers 14a and 14b, a synchronization detection unit 15 as synchronization detection means, and laser light sources LD0 and LD1.

The data control apparatus 20 outputs an image signal for controlling the laser light source drivers 14a and 14b so as to control a laser beam write

operation performed by the optical scanning apparatus 10.  
The data control apparatus 20 comprises pulse train  
generating units 21a and 21b serving as phase control  
means, clock generating units 22a and 22b serving as  
5 pixel clock generation means, an image data processing  
unit 23, a register 24, and shift generating units 26a  
and 26b.

The CPU 30 is a microcomputer comprising a  
central processing unit, a program ROM, etc., and  
10 generally controls an engine unit (a main part of the  
image forming apparatus) including the optical scanning  
apparatus 10 and the data control apparatus 20. The CPU  
30 outputs information input from the operation unit 15,  
and sets the information in the register 24. The CPU 30  
15 serves as scan time comparison means and setting value  
computation means.

The printer controller 40 sends image data of  
a page unit to the image data processing unit 23 for  
each line (one scan line) as an image signal (video  
20 signal)

The register 24 according to the present  
embodiment retains initial shift setting values osft0  
and osft1, which are previously set by the CPU 30.

Additionally, the image forming apparatus  
25 according to the present embodiment has the shift

generating units 26a and 26b in addition to the structure of the image forming apparatus according to the first embodiment of the present invention. The shift generating units 26a and 26b generate shift signals sft0 and sft1 by using the above-mentioned initial shift setting values osft0 and osft1 for changing positions of the phase change of the pixel clocks clkw0 and clkwl, respectively, and outputs the shift signals sft0 and sft1 to the respective pulse train generating units 21a and 21b.

A description will now be given, with reference to FIG. 24, of a structure and an operation of the shift generating units 26a and 26b according to the fifth embodiment of the present invention. FIG. 24 is a block diagram of the shift generating units 26a and 26b according to the fifth embodiment of the present invention.

The shift generating unit 26a comprises a counter 301 and a computing unit 302. The counter 301 counts up or increments (+1) a count value p each time the clear signal xlclr0 is supplied from the clock generating unit 22a. That is, the counter 301 counts a number of lines extending in the sub-scanning direction (number of times of the main scanning), and outputs the count value p. The computing unit 302 computes the

shift signal sft0 by applying an arithmetic process to the initial shift signal (initial shift setting value) sft0 supplied from the register 24 in accordance with the count value p supplied by the counter 301, and  
5 outputs the shift signal sft0 to the pulse generating unit 21a.

The shift generating unit 26b comprises a counter 311 and a computing unit 312. The counter 311 counts up or increments (+1) a count value q each time  
10 the clear signal xlclr1 is supplied from the clock generating unit 22b. That is, the counter 311 counts a number of lines extending in the sub-scanning direction (number of times of the main scanning), and outputs the count value q. The computing unit 302 computes the  
15 shift signal sft1 by applying an arithmetic process to the initial shift signal (initial shift setting value) sft1 supplied from the register 24 in accordance with the count value q supplied by the counter 311, and  
outputs the shift signal sft1 to the pulse generating  
20 unit 21b.

A description will now be given, with reference to FIG. 25, of a structure and an operation of the pulse train generating units 21a and 21b according to the fifth embodiment of the present invention. FIG.  
25 25 is a block diagram of the pulse train generating

units 21a and 21b according to the fifth embodiment of the present invention. It should be noted that the structure and the operation of the pulse train generating units 21a and 21b according to the present  
5 embodiment are the same as that of the first embodiment except for the parts specifically described below.

The pulse train generating unit 21a comprises comparators 101 and 102, counters 103 and 104, and AND circuits 105 and 106. The pulse train generating unit  
10 21b comprises comparators 111 and 112, counters 113 and 114, and AND circuits 115 and 116.

The present embodiment differs from the first embodiment in that the shift signals sft0 and sft1 are input to the counters 103 and 113 from the shift  
15 generating units 26a and 26b, respectively. The output timings of the external pulse trains xpls0 and xpls1 from the pulse train generating units 21a and 21b are shifted (delayed) by the shifts values SFT0 and SFT1, respectively, by the counters 103 and 113 delaying a  
20 start of the counting operation on the pixel clocks clkw0 and clkwl by shift values SFT0 and SFT1, which are indicated by the input shift signals sft0 and sft1, respectively.

A description will be given below of a  
25 shifting operation on the external pulse trains xpls0

and xpls1. Here, it is supposed that there is the following relationship between the interval of xlclr0, the interval prd0 of generation of the pulse xpls0, the number num0 of the pluses of the pulse xpls0 and the amount of shift (here, indicated by "SFT0") indicated by the shift signal sft0.

Interval of xlclr0 > prd0 × xnum0 + SFT0  
Accordingly, the amount of shift SFT0 is smaller than (xlclr0 interval - prd0 × num0). If a process of shifting the external pulse train xpls0 for each line (one scan line) is performed, and produce a pattern in which the process of shifting is repeated four times and then return to the original external pulse train xpls0, the CPU 30 sets the initial shift setting value osft0 in the shift register 24 as data (xlclr0 interval - prd0×num0) × 1/4.

The computing unit 302 outputs the shift signal sft0 each time the counter 301 counts up the count value p (+1). In this example, a product of the count value p and the initial setting value osft0 is computed each time the count up occurs.

FIG. 26 is a time chart showing a shift of the external pulse train xpls0 in a case where the initial shift setting value osft0 is set to (xlclr0 interval - prd0×num0) × 1/4 in the fifth embodiment of the present



invention. As shown in FIG. 26,  $osft0$  is output as the shift signal  $sft0$  for a first count-up ( $p=1$ ), twice the value of  $osft0$  is output as the shift signal  $sft0$  for a second count-up ( $p=2$ ), three times the value of  $osft0$  is  
5 output as the shift signal  $sft0$  for a third count-up ( $p=3$ ), and four times the value of  $osft0$  is output as the shift signal  $sft0$  for a fourth count-up ( $p=4$ ). Then, if the count value  $p$  supplied from the counter 301 becomes equal to "5", that is, if the product of the  
10 count value  $p$  and  $osft0$  exceeds ( $xlclr$  interval -  $prd0 \times num0$ ), the count value of the counter 301 is cleared (reset) to "0", and, thus, the amount of shift indicated by the shift signal  $sft0$  is set to "0" so as to repeat the above-mentioned operation.

15 Thus, the pulse train generating unit 21a can sequentially output the external pulse train  $xpls0$  of which phase is shifted by the value of the shift signal  $sft0$  for each line.

The case where the initial shift setting value  
20  $osft0$  is set to ( $xlclr0$  interval -  $prd0 \times num0$ )  $\times 1/4$  has been explained above.

A description will be given below, as another example, of a case where the initial shift setting value  $osft0$  is set to ( $xlclr0$  interval -  $prd0 \times num0$ )  $\times 3/7$ .

25 FIG. 27 is a time chart showing a shift of the

external pulse train  $xpls0$  in a case where the initial shift setting value  $osft0$  is set to  $(xlclr0 \text{ interval} - prd0 \times num0) \times 3/7$  in the fifth embodiment of the present invention. As shown in FIG. 27,  $osft0$  is output as the shift signal  $sft0$  for a first count-up ( $p=1$ ), twice the value of  $osft0$  is output as the shift signal  $sft0$  for a second count-up ( $p=2$ ), three times the value of  $osft0$  is output as the shift signal  $sft0$  for a third count-up ( $p=3$ ), and goes on. Here, when three times the value of  $osft0$  ( $osft0 \times 3$ ) is set to  $(xlclr0 \text{ interval} - prd0 \times num0) \times 9/7$ , it exceeds  $(xlclr \text{ interval} - prd0 \times num0)$ . In this case, since the count value  $p$  of the counter 301 is cleared (reset) to "0" when the value of  $osft0 \times n$  exceeds  $(xlclr \text{ interval} - prd0 \times num0)$ , the amount of shift indicated by the shift signal  $sft0$  is set to  $(xlclr0 \text{ interval} - prd0 \times num0) \times 2/7$  so as to continue the shifting operation.

As mentioned above, the count value  $p$  of the counter 301 is cleared to "0" when  $(xlclr0 \text{ interval} - prd0 \times num0)$  exceeds (or matches) the value of the product of the count value  $p$  and the initial shift setting value  $osft0$ . Thus, when the initial shift setting value  $osft0$  is set to  $(xlclr0 \text{ interval} - prd0 \times num0) \times 3/7$ , the shift value is sequentially set to the following values:

$(xlclr0 \text{ interval} - prd0 \times num0) \times 3/7$  ( $p=1$ );

(xlclr0 interval - prd0×num0) × 6/7 (p=2);  
(xlclr0 interval - prd0×num0) × 2/7 (p=3);  
(xlclr0 interval - prd0×num0) × 5/7 (p=4);  
(xlclr0 interval - prd0×num0) × 1/7 (p=5);  
5 (xlclr0 interval - prd0×num0) × 4/7 (p=6); and  
(xlclr0 interval - prd0×num0) × 7/7 (p=7), at which  
the value is cleared to "0".

As mentioned above, if the initial shift  
setting value osft0 is set to (xlclr0 interval -  
10 prd0×num0) × A/B (A and B are prime numbers), the pulse  
generating timing of the external pulse train returns to  
the original generating timing (p=0 or q=0) when the  
count value p (or q) becomes equal to B. Therefore, as  
the denominator "B" is set to a larger number, the  
15 number of lines in the sub-scanning direction after the  
shift is started and until the shift is returned to the  
pattern of the original external pulse train xpls0 can  
be larger. Therefore, if a pattern formed in the output  
image due to the phase change of the pixel clock is  
20 highly visible, it can be made to invisible by setting  
the above-mentioned number "B" to a larger number by  
using the operation unit 50, thereby improving the image  
quality.

Although the image forming apparatus according  
25 to the present embodiment uses the two laser light beams

LD0 and LD1, the number of laser light sources is not limited to two and U laser light sources (U is an integer greater than 2) may be used. In such a case, the shift generating unit for generating the shift value is provided for each laser light source so as to shift the output timing of the external pulse train for changing the phase of the laser beam of each laser light source. Additionally, the register 24 retains the initial shift setting value for each laser light source.

Moreover, although the present embodiment corresponds to the image forming apparatus according to the first embodiment, which is provided with an additional function (structure) of shifting the output timing of the external pulse train, such a function (structure) may be provided to the image forming apparatus according to the second embodiment or the fourth embodiment.

In the present embodiment, the image forming apparatus can shift the timing to perform the phase change of the laser beam of each laser light source for each scan of the laser beam so as to vary the timing, and, thus, the write magnification correction is more effective in a case of a plurality of lines. That is, formation of a pattern such as a highly visible line in an output image (side effects which are highly visible

in the output image) can be positively prevented.  
Therefore, an image design can be performed more in real size, and it becomes possible to further improve an image quality.

5

(Sixth Embodiment)

In the image forming apparatus according to the first embodiment of the present invention, the interval prd0 and prd1 of generation of the pulses of the external pulse trains and the number num0 and num1 of the pulses of the external pulse trains are set over an entire main-scanning line. On the other hand, in an image forming apparatus according to a sixth embodiment of the present embodiment, 1 main-scanning line is  
10 divided into a plurality of sections so that an interval of generation of pulses and a number of pulses of the external pulse train are set on an individual section basis.  
15

A description will now be given, with  
20 reference to FIG. 28, of a structure of the image forming apparatus according to the sixth embodiment of the present invention. FIG. 28 is a block diagram of the image forming apparatus according to the sixth embodiment of the present invention. It should be noted  
25 that the structure and operation of the image forming

apparatus according to the present embodiment are the same as that of the image forming apparatus according to the first embodiment except for the parts specifically described below.

5           As shown in FIG. 28, the image forming apparatus comprises an optical scanning apparatus 10, a data control apparatus 20, a CPU 30, a printer controller 40, and an operation unit 50. It should be noted that the structure of the image forming apparatus  
10 shown in FIG. 28 is simplified, and the image forming apparatus may have structural parts other than the parts shown in FIG. 28.

          The optical scanning apparatus 10 uses laser beams to form an image, and comprises a photoconductor  
15 11 serving as a medium to be scanned, an f $\theta$  lens 12, a polygon mirror 13 serving as rotational deflection means, laser light source drivers 14a and 14b, a synchronization detection unit 15 as synchronization detection means, and laser light sources LD0 and LD1.

20           The data control apparatus 20 outputs an image signal for controlling the laser light source drivers 14a and 14b so as to control a laser beam write operation performed by the optical scanning apparatus 10. The data control apparatus 20 comprises pulse train  
25 generating units 21a and 21b serving as phase control

means, clock generating units 22a and 22b serving as pixel clock generation means, an image data processing unit 23, a register 24, and shift generating units 26a and 26b.

5                   FIG. 29 is a circuit diagram of the pulse train generating unit 21a according to the sixth embodiment of the present invention. FIG. 30 is a circuit diagram of the pulse train generating unit 21b according to the sixth embodiment of the present  
10 invention. The structures and operations of the pulse train generating unit 21a and the pulse train generating unit 21b are the same with each other, and here the structure and operation of the pulse train generating unit 21a will be described below with reference to FIG.  
15 29.

                  The pulse train generating unit 21a shown in FIG. 29 comprises a counter 401; L comparators 402-1, 402-2, ..., 402-(L-1), and 402-L; L circuit groups 403-1, 403-2, ..., 403-(L-1), and 403-L; and an OR-circuit 404.  
20 The counter 401 receives the clear signal  $xlclr0$  generated from the synchronization detection signal  $detp$  by the clock generating unit 22a, counts the number of the pixel clocks  $clkw0$  on the basis of the input time, and outputs a count value  $k0$ . The count value  $k0$  is  
25 used so as to divide 1 scanning period defined by the

polygon mirror 13 into a plurality of periods and to set each period as a divided period.

The comparators 402-1, 402-2, ..., 402-(L-1), and 402-L are previously provided with start point values (a first start point value to an Lth start point value) of the divided periods (a first divided period to an Lth divided period) so as to compare the count value k0 with the start point values, respectively, and outputs a corresponding one of area signals (a first area signal to an Lth area signal) when the count value k0 reaches each of the start values. The start value of each of the divided periods is set according to start point signals (a first start point signal to an Lth start point signal) supplied by the CPU 30 to the respective comparators 402-1, 402-2, ..., 402-(L-1), and 402-L.

For example, the comparator 402-1 compares the count value k0 of the counter 401 with the start point value (first start point value) of the first divided period, and outputs the first area signal area01 when the count value k0 reaches the first start point value (start01). Similarly, the comparator 402-2 compares the count value k0 of the counter 401 with the start point value (second start point value) of the second divided period, and outputs the second area signal area02 when



the count value  $k_0$  reaches the second start point value (start02).

Each of the circuit groups 403-1, 403-2, ..., 403-(L-1), and 403-L is constituted parts that same as that shown in FIG. 5 (that is, the pulse train generating unit 21a or 21b), and performs an operation the same as the above-mentioned pulse generating operation explained with reference to FIG. 6. However, the clear signal  $xclr_0$  is replaced by the area signal.

Accordingly, for example, the first area signal  $ara_01$  is input to the circuit group 403-1 instead of the clear signal  $xclr_0$ , and the second area signal  $ara_02$  is input to the circuit group 403-2 instead of the clear signal  $xclr_0$ . Moreover, the arbitrary pulse generation interval (setting value)  $prd_1, prd_2, \dots, prd_{L-1}, prd_L$  and pulse number (setting value)  $num_1, num_2, \dots, num_{L-1}, num_L$  are set to the circuit groups 403-1, 403-2, ..., 403-(L-1), and 403-L, respectively. When the OR circuit 404 receives the external pulse train  $xpls_0$  from any one of the circuit groups 403-1, 403-2, ..., 403-(L-1), and 403-L, the OR circuit 404 outputs the external pulse train  $xpls_0$  without change.

A description will now be given, with reference to FIG. 31, of an operation of the pulse train generating unit 21a haven the above-mentioned structure.

FIG. 31 is a flowchart of a pulse generating operation performed by the pulse generating unit 21a according to the sixth embodiment of the present invention. When a power is turned on, in the pulse train generating unit 21a, the counter 401 resets the count value k0 to "1" (step S601). Thereafter, upon reception of the clear signal xlclr0 (Yes of step S602), the counter 401 counts up or increments (+1) each time the pixel clock clkw0 is input (step S603). Then, each time the count value k0 reaches the start point values (start01, start02, and ..., start0L-1, and start0L) of the divided periods (steps S604-S607), the respective comparators 402-1, 402-2, ..., 402-(L-1), and 402-L output the respective first to Lth area signals (area01, area02, ..., area0L-1, area0L) (steps S608-S611).

Each of the circuit groups 403-1, 403-2, ..., 403-(L-1), and 403-L performs an operation the same as the above-mentioned pulse generating operation of the pulse train generating unit 21a (steps S608-S611).

In this case, since the count value k0 of the counter 401 first reaches the start point value start1 of the first divided period, the comparator 402-1 outputs the area signal area01 at that time. Then, the circuit group 403-1 performs the operation the same as the above-mentioned pulse generating operation by using

the parts (refer to FIG. 5) including the internal  
counters 103 and 104 so as to generate the external  
pulse train xpls0 corresponding to the first divided  
period and output the external pulse train xpls0 to the  
5 OR-circuit 404. The external pulse train xpls0 is  
output via the OR-circuit 404.

Then, since the count value k0 of the counter  
401 reaches the start point value start02 of the second  
divided period, the comparator 402-2 outputs the area  
10 signal area02 at that time. Then, the circuit group  
403-2 performs an operation the same as the above-  
mentioned pulse generating operation using each part  
containing the internal counters 103 and 104 so as to  
generate the external pulse train xpls0 corresponding to  
15 the second divided period and output the generated  
external pulse train xpls0 to the OR circuit 404. The  
external pulse train xpls0 is also output through via  
the OR-circuit 404.

Thereafter, operations the same as the above-  
20 mentioned operation are performed until the Lth divided  
period is reached, and, finally, the external pulse  
train xpls0 corresponding to the Lth divided period is  
generated by the circuit group 403-L and is output via  
the OR circuit 404. In this way, the external pulse  
25 train (the last external pulse train) XPLS0 finally

output from the OR circuit 404 turns into a pulse train containing the external pulse train  $xpls0$  consisting of an arbitrary number of pulses in each divided period (area) as shown in FIG. 32.

5                    Similarly, in the pulse train generating unit 21b, the start point values (the first to Lth start point values) of the divided periods (the first to Lth divided periods) are set beforehand to the comparators 412-1, 412-2, . . . . , 412-(L-1), and 412-L, respectively.

10    Then, the count value  $k1$  of the counter 411 is compared with the start point values, and when the count value reaches the start point values, the area signals (the first to Lth area signals) are output, respectively.

          The start point values of the divided periods are set by

15    the start signals (the first to Lth start signals) input by the CPU 30 to the comparators 412-1, 412-2, . . . . , 412-(L-1) and 412-L, respectively. Similarly, a process of generating the external pulse train  $xpls1$  the same as that of the pulse generating unit 21a is performed in

20    the pulse train generating unit 21b.

          Although the image forming apparatus according to the present embodiment uses two laser light sources LD0 and LD1 to perform a scanning operation, U laser light sources (U is an integer greater than two) may be

25    used to perform a scanning operation. In this case, the

laser light source driver, the pulse train generating unit and the clock generating unit are provided for each laser light source, and a main-scanning line of each laser light source is divided into a plurality of sections (areas) and a setting value is set to each of the divided areas so as to change the phase of the pixel clock of each laser light source.

Additionally, although the image forming apparatus according to the present embodiment is achieved by adding the function (structure) of changing a phase of a pixel clock of each laser light source to the image forming apparatus according to the first embodiment by dividing the main-scanning line of the laser beam of each laser light source and setting the setting value for each divided area, such a function (structure) may be added to the image forming apparatus according to the second through fifth embodiments.

As mentioned above, the pulse train generating units 21a and 21b are capable of performing the phase change (phase setting) of the pixel clock  $clk_w0$  by using the final external pulse train  $XPLS0$  containing the external pulse train  $xpls0$  generated for each of the first to  $L$ th divided periods by dividing one scan period by the polygon mirror 13 into the plurality of sections (first to  $L$ th divided areas). Therefore, the image

forming apparatus according to the present embodiment is capable of performing the write magnification locally with respect to the pixel clocks clkw0 and clkw1 by using the respective external pulse trains xpls0 and  
5 xpls1 corresponding to each divided period. Thus, an image design of a real size can be performed and the image quality can be improved.

(Seventh Embodiment)

10 A description will now be given, with reference to FIG. 33, of a structure of an image forming apparatus according to a seventh embodiment of the present invention. FIG. 33 is a block diagram of the image forming apparatus according to the seventh  
15 embodiment of the present invention. It should be noted that the structure and operation of the image forming apparatus according to the present embodiment are the same as that of the image forming apparatus according to the first embodiment except for the parts specifically  
20 described below.

As shown in FIG. 33, the image forming apparatus comprises an optical scanning apparatus 10, a data control apparatus 20, a CPU 30, a printer controller 40, and an operation unit 50. It should be  
25 noted that the structure of the image forming apparatus

shown in FIG. 33 is simplified, and the image forming apparatus may have structural parts other than the parts shown in FIG. 33.

The optical scanning apparatus 10 uses laser beams to form an image, and comprises a photoconductor 11 serving as a medium to be scanned, an  $f\theta$  lens 12, a polygon mirror 13 serving as rotational deflection means, laser light source drivers 14a and 14b, a synchronization detection unit 15 as synchronization detection means, clock generating units 22a and 22b serving as pixel clock generation means, and laser light sources LD0 and LD1.

The data control apparatus 20 outputs an image signal for controlling the laser light source drivers 14a and 14b so as to control a laser beam write operation performed by the optical scanning apparatus 10. The data control apparatus 20 comprises pulse train generating units 21a and 21b serving as phase control means, an image data processing unit 23, a register 24, and shift generating units 26a and 26b.

The CPU 30 serves as scan time comparison means and setting value computation means.

#### (Eighth Embodiment)

A description will now be given, with

reference to FIG. 34, of a structure of an image forming apparatus according to an eighth embodiment of the present invention. FIG. 34 is a block diagram of the image forming apparatus according to the eighth  
5 embodiment of the present invention. It should be noted that the structure and operation of the image forming apparatus according to the present embodiment are the same as that of the image forming apparatus according to the second embodiment except for the parts specifically  
10 described below.

As shown in FIG. 34, the image forming apparatus comprises an optical scanning apparatus 10, a data control apparatus 20, a CPU 30, a printer controller 40, and an operation unit 50. It should be  
15 noted that the structure of the image forming apparatus shown in FIG. 34 is simplified, and the image forming apparatus may have structural parts other than the parts shown in FIG. 34.

The optical scanning apparatus 10 uses laser  
20 beams to form an image, and comprises a photoconductor 11 serving as a medium to be scanned, an  $f\theta$  lens 12, a polygon mirror 13 serving as rotational deflection means, laser light source drivers 14a and 14b, a synchronization detection unit 15 serving as  
25 synchronization detection means, a front-end



synchronization detection unit 16 and a rear-end  
synchronization detection unit 17 both serving as  
synchronization detection means, clock generating units  
22a and 22b serving as pixel clock generation means, and  
5 laser light sources LD0 and LD1.

The data control apparatus 20 outputs an image  
signal for controlling the laser light source drivers  
14a and 14b so as to control a laser beam write  
operation performed by the optical scanning apparatus 10.  
10 The data control apparatus 20 comprises pulse train  
generating units 21a and 21b serving as phase control  
means, an image data processing unit 23, a register 24,  
and scan time measuring units 25a and 25b serving as  
scan time measuring means.

15 The CPU 30 serves as scan time comparison  
means and setting value computation means.

(Ninth Embodiment)

A description will now be given, with  
20 reference to FIG. 35, of a structure of an image forming  
apparatus according to a ninth embodiment of the present  
invention. FIG. 35 is a block diagram of the image  
forming apparatus according to the ninth embodiment of  
the present invention. It should be noted that the  
25 structure and operation of the image forming apparatus

according to the present embodiment are the same as that of the image forming apparatus according to the third embodiment except for the parts specifically described below.

5           As shown in FIG. 35, the image forming apparatus comprises an optical scanning apparatus 10, a data control apparatus 20, a CPU 30, a printer controller 40, and an operation unit 50. It should be noted that the structure of the image forming apparatus  
10 shown in FIG. 35 is simplified, and the image forming apparatus may have structural parts other than the parts shown in FIG. 35.

          The optical scanning apparatus 10 uses laser beams to form an image, and comprises a photoconductor  
15 11 serving as a medium to be scanned, an  $f\theta$  lens 12, a polygon mirror 13 serving as rotational deflection means, laser light source drivers 14a and 14b, a synchronization detection unit 15 as synchronization detection means, clock generating units 22a and 22b  
20 serving as pixel clock generation means, and laser light sources LD0 and LD1.

          The data control apparatus 20 outputs an image signal for controlling the laser light source drivers 14a and 14b so as to control a laser beam write  
25 operation performed by the optical scanning apparatus 10.

The data control apparatus 20 comprises pulse train generating units 21a and 21b serving as phase control means, an image data processing unit 23, and a register 24.

5                   The CPU 30 serves as scan time comparison means and setting value computation means.

(Tenth Embodiment)

A description will now be given, with  
10   reference to FIG. 36, of a structure of an image forming apparatus according to a tenth embodiment of the present invention. FIG. 36 is a block diagram of the image forming apparatus according to the tenth embodiment of the present invention. It should be noted that the  
15   structure and operation of the image forming apparatus according to the present embodiment are the same as that of the image forming apparatus according to the fourth embodiment except for the parts specifically described below.

20                   As shown in FIG. 36, the image forming apparatus comprises an optical scanning apparatus 10, a data control apparatus 20, a CPU 30, a printer controller 40, and an operation unit 50. It should be noted that the structure of the image forming apparatus  
25   shown in FIG. 36 is simplified, and the image forming

apparatus may have structural parts other than the parts shown in FIG. 36.

The optical scanning apparatus 10 uses laser beams to form an image, and comprises a photoconductor 11 serving as a medium to be scanned, an  $f\theta$  lens 12, a polygon mirror 13 serving as rotational deflection means, laser light source drivers 14a and 14b, a front-end synchronization detection unit 16 and a rear-end synchronization detection unit 17 both serving as synchronization detection means, clock generating units 22a and 22b serving as pixel clock generation means, and laser light sources LD0 and LD1.

The data control apparatus 20 outputs an image signal for controlling the laser light source drivers 14a and 14b so as to control a laser beam write operation performed by the optical scanning apparatus 10. The data control apparatus 20 comprises pulse train generating units 21a and 21b serving as phase control means, an image data processing unit 23, a register 24, and a scan time measuring unit 25a serving as scan time measuring means.

The CPU 30 serves as scan time comparison means and setting value computation means.

(Eleventh Embodiment)

A description will now be given, with reference to FIG. 37, of a structure of an image forming apparatus according to an eleventh embodiment of the present invention. FIG. 37 is a block diagram of the  
5 image forming apparatus according to the eleventh embodiment of the present invention. It should be noted that the structure and operation of the image forming apparatus according to the present embodiment are the same as that of the image forming apparatus according to  
10 the fifth embodiment except for the parts specifically described below.

As shown in FIG. 37, the image forming apparatus comprises an optical scanning apparatus 10, a data control apparatus 20, a CPU 30, a printer  
15 controller 40, and an operation unit 50. It should be noted that the structure of the image forming apparatus shown in FIG. 37 is simplified, and the image forming apparatus may have structural parts other than the parts shown in FIG. 37.

20 The optical scanning apparatus 10 uses laser beams to form an image, and comprises a photoconductor 11 serving as a medium to be scanned, an  $f\theta$  lens 12, a polygon mirror 13 serving as rotational deflection means, laser light source drivers 14a and 14b, a  
25 synchronization detection unit 15 as synchronization

detection means, clock generating units 22a and 22b serving as pixel clock generation means, and laser light sources LD0 and LD1.

The data control apparatus 20 outputs an image  
5 signal for controlling the laser light source drivers  
14a and 14b so as to control a laser beam write  
operation performed by the optical scanning apparatus 10.  
The data control apparatus 20 comprises pulse train  
generating units 21a and 21b serving as phase control  
10 means, an image data processing unit 23, a register 24,  
and shift generating units 26a and 26b.

The CPU 30 serves as scan time comparison  
means and setting value computation means.

15 (Twelfth Embodiment)

A description will now be given, with  
reference to FIG. 38, of a structure of an image forming  
apparatus according to a twelfth embodiment of the  
present invention. FIG. 38 is a block diagram of the  
20 image forming apparatus according to the twelfth  
embodiment of the present invention. It should be noted  
that the structure and operation of the image forming  
apparatus according to the present embodiment are the  
same as that of the image forming apparatus according to  
25 the sixth embodiment except for the parts specifically

described below.

As shown in FIG. 38, the image forming apparatus comprises an optical scanning apparatus 10, a data control apparatus 20, a CPU 30, a printer controller 40, and an operation unit 50. It should be noted that the structure of the image forming apparatus shown in FIG. 38 is simplified, and the image forming apparatus may have structural parts other than the parts shown in FIG. 38.

10           The optical scanning apparatus 10 uses laser beams to form an image, and comprises a photoconductor 11 serving as a medium to be scanned, an  $f\theta$  lens 12, a polygon mirror 13 serving as rotational deflection means, laser light source drivers 14a and 14b, a  
15           synchronization detection unit 15 as synchronization detection means, clock generating units 22a and 22b serving as pixel clock generation means, and laser light sources LD0 and LD1.

          The data control apparatus 20 outputs an image  
20           signal for controlling the laser light source drivers 14a and 14b so as to control a laser beam write operation performed by the optical scanning apparatus 10. The data control apparatus 20 comprises pulse train generating units 21a and 21b serving as phase control  
25           means, an image data processing unit 23, and a register

24.

The CPU 30 serves as scan time comparison means and setting value computation means.

5 (Differences between the first through sixth embodiments and the seventh to twelfth embodiments)

A description will now be given of differences between first through sixth embodiments and the seventh to twelfth embodiments. In the first through sixth  
10 embodiments, the clock generating units 22a and 22b are provided in the data control apparatus 20. On the other hand, the clock generating units 22a and 22b in the seventh through twelfth embodiments are provided in the optical scanning equipment 10.

15 In the first through sixth embodiments, the clock generating unit 22a outputs the pixel clock clkw0 and the clear signal xlclr0 to the pulse train generating section 21a and the image data processing section 23. On the other hand, the clock generating  
20 unit 22a in the seventh through twelfth embodiments output the pixel clock clkw0 and the clear signal xlclr0 to the pulse train generating unit 21a.

In the first through sixth embodiments, the clock generating unit 22b outputs the pixel clock clkw1  
25 and the clear signal xlclr1 to the pulse train



generating unit 21b and the image data processing unit  
23. On the other hand, the clock generating section 22b  
in the seventh through twelfth embodiment output the  
pixel clock clkwl and the clear signal xlclrl to the  
5 pulse train generating unit 21b.

In the first through sixth embodiments, the  
image data processing unit 23 outputs the image signals  
input from the printer controller 40 to the laser light  
source drivers 14a and 14b in synchronization with the  
10 pixel clocks clkw0 and clkwl from the clock generating  
units 22a and 22b. On the other hand, in the seventh  
through twelfth embodiments, the image data processing  
unit 23 outputs the image signals data0 and data1 input  
from the printer controller 40 to the clock generating  
15 units 22a and 22b, respectively. The clock generating  
unit 22a outputs the input image signal data0 to the  
laser light source driver 14a in synchronization with  
the generated pixel clock clkw0. The laser light source  
driver 14a outputs a drive control signal for  
20 controlling ON/OFF of luminescence to the laser light  
source LD0 according to the contents of data of the  
picture signal data0 according to the input timing of  
the image signal data0 based on the pixel clock clkw0  
after phase change. Additionally, the clock generating  
25 unit 22b outputs the input image signal data1 to the

laser light source driver 14b in synchronization with  
the generated pixel clock clkwl. Laser light source  
driver 14b outputs a drive control signal for  
controlling ON/OFF of luminescence to the laser light  
5 source LD1 according to the contents of data of the  
image signal data1 according to the input timing of the  
image signal data1 based on the pixel clock clkwl after  
phase change.

As mentioned above, in the image forming  
10 apparatuses of the first through twelfth embodiments  
provided with two or more laser light sources, the laser  
light sources may write latent images of the toner  
images in the same color or write latent images in  
different colors such as yellow, magenta, cyan and black.

15 Moreover, the image forming apparatuses  
performs: a process of data writing; a process of data  
reading; a process of computing a number of pulses to be  
increased or decreased in accordance with a time period  
from a time when one synchronization detection means  
20 detects a laser beam to a time when another  
synchronization detection means detects the laser beam;  
a process of computing setting values of the laser light  
sources by adding the difference setting values to the  
setting values of one of the laser light sources that  
25 are input or computed; and a process of determining

whether or not the measured values of the laser light sources are supplied. Although the above-mentioned processes are performed by a computer program (CPU 30) installed in the image forming apparatus, such a program  
5 may be recorded on a recording medium such as an optical recording medium, a magnetic recording medium, a magneto-optical recording medium or a semiconductor, and loaded to the image forming apparatus from the recording medium, or such a program may be downloaded to the image  
10 forming apparatus from an external apparatus which is connected to the image forming apparatus through a network such as a local area network or the Internet.

The present invention is not limited to the specifically disclosed embodiments, and variations and  
15 modifications may be made without departing from the scope of the present invention.

The present application is based on Japanese priority application No. 2003-54717 filed February 28, 2003, the entire contents of which are hereby  
20 incorporated by reference.